Ref. No. 3963
082006

# ONKYO SERVICE MANUAL

## CD RECEIVER

## MODEL CR-315
## MODEL CR-315DAB






RC-660S

### CR-315 for CS-315 Black and Silver models

| | |
|---|---|
| B MPP, S MPP | 230V AC, 50Hz |
| S MDC | 120V AC, 60Hz |

### CR-315 Silver model

| | |
|---|---|
| S MGT, S MGQ | 220 - 230V AC, 50/60Hz |
| S MDT | 120V AC, 60Hz |

### CR-315DAB for CS-315UK Silver model

| | |
|---|---|
| S MPB | 230V AC, 50Hz |

### SAFETY-RELATED COMPONENT WARNING!!


**COMPONENTS IDENTIFIED BY MARK ⚠ ON THE SCHEMATIC DIAGRAM AND IN THE PARTS LIST ARE CRITICAL FOR RISK OF FIRE AND ELECTRIC SHOCK. REPLACE THESE COMPONENTS WITH ONKYO PARTS WHOSE PART NUMBERS APPEAR AS SHOWN IN THIS MANUAL.**

**MAKE LEAKAGE-CURRENT OR RESISTANCE MEASUREMENTS TO DETERMINE THAT EXPOSED PARTS ARE ACCEPTABLY INSULATED FROM THE SUPPLY CIRCUIT BEFORE RETURNING THE APPLIANCE TO THE CUSTOMER.**

ONKYO®
IMAGINATIVE SIGHT & SOUND

www.audiodna.sk

# EXPLODED VIEW





www.audiodna.sk

CR-315/315DAB

# EXPLODED VIEWS OF MECHANISM-1

## CD MECHANISM : DLM1A01-14CA / KSM-213CLCM

**<Note>**
CD MECHANISM =
Tray loading unit : "DLM1A01-14CA"
+ Drive unit : "KSM-213CLCM"





## PARTS LIST

| REF. NO. | PART NO. (SN) | PART NAME | DESCRIPTION | Q'TY |
|---|---|---|---|---|
| Z005 | 24800056 | CD Tray Loading unit | DLM1A01-14CA | 1 |
| Z006 | 24800017 | CD Drive unit | KSM-213CLCM | 1 |
| Z007 | 24818058 | INSULATOR | (CDC-A) | 4 |
| Z008 | 24820071 | SPRING | TP-D (silver) | 2 |
| Z009 | 24820072 | SPRING | TP-E (gold) | 2 |
| Z010 | 801632 | SCREW | 2.6 x 8 x W10 | 4 |

# EXPLODED VIEWS OF MECHANISM-2

## CD TRAY LOADING UNIT : DLM1A01-14CA





## PARTS LIST


| REF. NO. | PART NO. (SN) | DESCRIPTION | Q'TY |
|---|---|---|---|
| 1 | 65-210-1054 | CHASSIS | 1 |
| 2 | 65-218-1055 | TRAY | 1 |
| 3 | 65-211-2040 | SUB CHASSIS | 1 |
| 4 | 65-239-2004 | CAM SLIDER | 1 |
| 5 | 65-222-3005 | GEAR TRAY | 1 |
| 6 | 65-093-4057H | CLAMPER ASS'Y | 1 |
| 7 | 65-093-4058H | PWB ASS'Y | 1 |
| 8 | 65-222-4037 | GEAR A | 1 |
| 9 | 65-222-4004 | PULLEY GEAR | 1 |
| 10 | 65-093-4068H | MOTOR ASS'Y | 1 |
| 11 | 02-083-4274 | LOADING BELT | 1 |
| 12 | GSP14A25027 | SCREW | 2 |

# EXPLODED VIEWS OF MECHANISM-3

## CD DRIVE UNIT : KSM-213CLCM




OK



NG



## PARTS LIST

| REF. NO. | PART NO. (SN) | DESCRIPTION | Q'TY |
|---|---|---|---|
| 51 | X-2625-877-1 | Motor chassis ass'y | 1 |
| 52 | X2625-769-1 | Motor gear ass'y | 1 |
| 53 | 2626-908-01 | Sled shaft | 1 |
| 54 | 24810023 | Gear (A) (S) | 1 |
| 55 | 7621-255-15 | P2 x 3, Screw | 2 |
| 56 | 24840008 | Leaf switch | 1 |
| 57 | 1639-678-12 | Motor PC board | 1 |
| 58 | 1-564-722-11 | Connector 6pin | 1 |
| 61 | 8848-483-05 | KSS-213C, Pickup | 1 |

www.audiodna.sk


# SCHEMATIC DIAGRAMS-1


## PRE-AMPLIFIER SECTION

NAAR-8931

**U01**

**PRE-AMPLIFIER PC BOARD**






NOTE

- THE COMPONENTS IDENTIFIED BY MARK ⚠ ARE CRITICAL FOR SAFETY REPLACE ONLY WITH PART NUMBER SPECIFIED.
- VOLTAGE (MEASURED WITH VOLTMETER) ⟨ ⟩ IS DC VOLTAGE.(NO INPUT SIGNAL).
- ALL PNP TRANSISTORS ARE EQUIVALENT TO 2SA1015-GR UNLESS OTHERWISE NOTED.
- ALL NPN TRANSISTORS ARE EQUIVALENT TO 2SC1815-GR UNLESS OTHERWISE NOTED.
- ALL DIODES ARE EQUIVALENT TO 1SS133 UNLESS OTHERWISE NOTED.
- ELECTROLYTIC CAPACITORS ( ⊣⊢ ) ARE IN uF/WV.
- ALL CAPACITORS ARE IN pF/50WV UNLESS OTHERWISE NOTED.
  EX) 030- 3pF 330- 33pF 331- 330pF 333- 0.033uF
- ALL RESISTORS ARE IN OHMS 1/4WATTS UNLESS OTHERWISE NOTED.
- THE THICK LINES ON PC BOARD ARE THE PRINTING SIDE OF THE PARTS.
  EX) ⊙⊙⊙ PRINTING SIDE
- CIRCUIT IS SUBJECT TO CHANGE FOR IMPROVEMENT.

<Note>


NC = No mount of parts.


SD-Z : XY

Location of connected terminal in schematic diagrams.
SD-Z = Schematic diagrams-Z. X = A to H, Y = 1 to 5.

# SCHEMATIC DIAGRAMS-2

## CD SECTION






www.audiodna.sk

# SCHEMATIC DIAGRAMS-3

## DISPLAY SECTION


**<Note>**

NC = No mount of parts.

SD-Z : XY

Location of connected terminal in schematic diagrams.

SD-Z = Schematic diagrams-Z. X = A to H, Y = 1 to 5.







CR-315/315DAB

# SCHEMATIC DIAGRAMS-4

## POWER SUPPLY SECTION




AC IN
MDC, MDT : 120V, 60Hz
MPP, MPB : 230V, 50Hz
MGT, MGQ : 220 - 230V, 50/60Hz

NOTE

- THE COMPONENTS IDENTIFIED BY MARK ⚠ ARE CRITICAL FOR SAFETY REPLACE ONLY WITH PART NUMBER SPECIFIED.
- VOLTAGE (MEASURED WITH VOLTMETER) ⟨ IS DC VOLTAGE.(NO INPUT SIGNAL).
- ALL PNP TRANSISTORS ARE EQUIVALENT TO 2SA1015-GR UNLESS OTHERWISE NOTED.
- ALL NPN TRANSISTORS ARE EQUIVALENT TO 2SC1815-GR UNLESS OTHERWISE NOTED.
- ALL DIODES ARE EQUIVALENT TO 1SS133 UNLESS OTHERWISE NOTED.
- ELECTROLYTIC CAPACITORS ( ) ARE IN uF/WV.
- ALL CAPACITORS ARE IN pF/50WV UNLESS OTHERWISE NOTED.
  EX) 030- 3pF 330- 33pF 331- 330pF 333- 0.033uF
- ALL RESISTORS ARE IN OHMS 1/4WATTS UNLESS OTHERWISE NOTED.
- THE THICK LINES ON PC BOARD ARE THE PRINTING SIDE OF THE PARTS.
  EX) PRINTING SIDE
- CIRCUIT IS SUBJECT TO CHANGE FOR IMPROVEMENT.

**<Note>**

NC = No mount of parts.

SD-Z : XY
Location of connected terminal in schematic diagrams.
SD-Z = Schematic diagrams-Z. X = A to H, Y = 1 to 5.

### CAUTION

FOR CONTINUED PROTECTION AGAINST FIRE HAZARD, REPLACE ONLY WITH FUSE OF SAME TYPE AND RATING INDICATED.

### ATTENTION

AFIN D'ASSURER UNE PROTECTION PERMANENTE CONTRE LES RISQUES D'INCENDIE, REMPLACER UNIQUEMENT PAR UN FUSIBLE DE MEME TYPE ET CALIBRATION COMME INDIQUE.

THIS SYMBOL LOCATED NEAR THE FUSE INDICATES THAT THE FUSE USED IS SLOW OPERATING TYPE FOR CONTINUED PROTECTION AGAINST FIRE HAZARD,REPLACE WITH SAME TYPE FUSE. FOR FUSE RATING REFER TO THE MARKING ADJACENT TO THE SYMBOL.

CE SYMBOLE INDIQUE QUE LE FUSIBLE UTLISE EST E LENT.POUR UNE PROTECTION PERMANENTE,N'UTILISER QUE DES FUSIBLES DE MEME TYPE. CE DARNIER EST INDIQUE LA QU LE PRESENT SYMBOL EST APPOSE.




CR-315/315DAB

# SCHEMATIC DIAGRAMS-5

## POWER AMPLIFIER SECTION

NAAF-8936 **U06**

**POWER AMPLIFIER PC BOARD**




NOTE

- THE COMPONENTS IDENTIFIED BY MARK ⚠ ARE CRITICAL FOR SAFETY REPLACE ONLY WITH PART NUMBER SPECIFIED.
- VOLTAGE (MEASURED WITH VOLTMETER) ⟨ ▭ ⟩ IS DC VOLTAGE.(NO INPUT SIGNAL).
- ALL PNP TRANSISTORS ARE EQUIVALENT TO 2SA1015-GR UNLESS OTHERWISE NOTED.
- ALL NPN TRANSISTORS ARE EQUIVALENT TO 2SC1815-GR UNLESS OTHERWISE NOTED.
- ALL DIODES ARE EQUIVALENT TO 1SS133 UNLESS OTHERWISE NOTED.
- ELECTROLYTIC CAPACITORS ( ⊣⊢ ) ARE IN uF/WV.
- ALL CAPACITORS ARE IN pF/50WV UNLESS OTHERWISE NOTED.
  EX) 030- 3pF 330- 33pF 331- 330pF 333- 0.033uF
- ALL RESISTORS ARE IN OHMS 1/4WATTS UNLESS OTHERWISE NOTED.
- THE THICK LINES ON PC BOARD ARE THE PRINTING SIDE OF THE PARTS.
  EX) ▭ PRINTING SIDE
- CIRCUIT IS SUBJECT TO CHANGE FOR IMPROVEMENT.

**<Note>**

NC = No mount of parts.


SD-Z : XY

Location of connected terminal in schematic diagrams.
SD-Z = Schematic diagrams-Z. X = A to H, Y = 1 to 5.

CR-315 MPP, MGT, MDT, MGQ
CR-315DAB MPB

NAETC-8939 **U09**


**SPEAKER TERMINAL PC BOARD**




CR-315 MDC

NAETC-8938 **U08**

**SPEAKER TERMINAL PC BOARD**







CR-315/315DAB

# PACKING PROCEDURE

## CR-315(S) MGT, MDT, MGQ

**<Note>**
CR-315(B) MPP, (S) MPP, MDC / CR-315DAB(S) MPB
---> Refer to service manual of "CS-315/315UK"



**CR-315/315DAB**

**NOTE : THE COMPONENTS IDENTIFIED BY THE MARK ! ARE CRITICAL FOR RISK OF FIRE AND ELECTRIC SHOCK. REPLACE ONLY WITH PART NUMBER SPECIFIED.**

**<Notes>**
<MGT> : Asian model
<MDT>: Taiwanese model
<MGQ> : Hong kong model

# PACKING PROCEDURE PARTS LIST

## CR-315 (S) MGT, MDT, MGQ

**<Note>**

CR-315(B) MPP,(S) MPP, MDC / CR-315DAB(S) MPB ---> Refer to service manual of "CS-315/315UK"

| | REF. NO. | PART NAME | DESCRIPTION | Q'TY | PART NO. (SN) | REMARKS |
|---|---|---|---|---|---|---|
| PV | A503 | PAD | (F & R / 1 set) | (1) | 29092332A | |
| PV | A504 | POLY BAG | POLY BAG (430 x 550) | 1 | 29100123C | |
| PV | A505 | TAPE | NITTO NO.29 | 1 | 29110149 | |
| PV | A507 | SHEET | --- | 1 | 29095906 | |
| PV | A508 | TAPE | SOP-400(CLEAR50MT)KO | 1 | 29110071 | |
| PV | A509 | CARTON | CR-315(S) | 1 | 29054572A | |
| PV | A511 | EAN LABEL | --- | 1 | 29364552 | |
| PV | A701 | POLY BAG | 350 x 200 x W250 | 1 | 29100201 | |
| PV | A801 | REMO CON | RC-660S | 1 | 24140660 | |
| PV | A803 | BATTERY | R6/AA(UM-3) | 2 | 3010194 | |
| PV | A803 or | BATTERY | R6/AA(UM-3) | (2) | 3010054 | |
| PV | A805 | INS MANUAL | En(CR-315) | 1 | 29344258A | |
| PV | A806 | INS MANUAL | Ct(CR-315) | 1 | 29344261A | |
| PV | A810 | FM ANT AS | Type W | 1 | 292191 | |
| PV | A811 | ANT COIL | NMA-3057 | 1 | 232140 | |
| PV | A817 | WRNTY CARD | MGQ | 1 | 29365099A | <MGQ> |
| PV | P905 | AC CORD | AS-CEE | 1 | 253299VOL | !, <MGT> |
| PV | P905 | AC CORD | AC-UC-2 | 1 | 253296VOL | !, <MDT> |
| PV | P905 | AC CORD | AS-BS | 1 | 253354LTK | !, <MGQ> |

www.audiodna.sk

**CR-315/315DAB**

**<Note>**
Parts marked by '**NSP**' are generally unavailable because they are not in our Master Spare Parts List.

**NOTE : THE COMPONENTS IDENTIFIED BY THE MARK ! ARE CRITICAL FOR RISK OF FIRE AND ELECTRIC SHOCK. REPLACE ONLY WITH PART NUMBER SPECIFIED.**

**<Notes>**
(B) : Black model only
(S) : Silver model only
<MPP> : CR-315 European model
<MDC> : CR-315 Canadian model
<MGT> : CR-315 Asian model
<MDT>: CR-315 Taiwanese model
<MGQ> : CR-315 Hong kong model
<DAB MPB> : CR-315DAB British model

## EXPLODED VIEW PARTS LIST

| | REF. NO. | PART NAME | DESCRIPTION | Q'TY | PART NO. (SN) | REMARKS |
|---|---|---|---|---|---|---|
| EV | A001 | F BRACKET | (B) | 1 | 27111462 | (B) |
| EV | A001 | F BRACKET | (S) | 1 | 27111461 | (S) |
| EV | A004 | SCREW | 3TTB+8B(CU)SR | 9 | 801618 | |
| EV | A007 | SCREW | 3TTB+8B(CU)SR | 2 | 801618 | |
| EV | A009 | CHASSIS | --- | 1 | --- | NSP |
| EV | A101 | REAR PANEL | CR-315 MPP | 1 | 27123605 | <MPP> |
| EV | A101 | REAR PANEL | CR-315 MDC | 1 | 27123609A | <MDC> |
| EV | A101 | REAR PANEL | CR-315 MPP | 1 | 27123605 | <MGT> |
| EV | A101 | REAR PANEL | CR-315 MPP | 1 | 27123605 | <MDT> |
| EV | A101 | REAR PANEL | CR-315 MPP | 1 | 27123605 | <MGQ> |
| EV | A101 | REAR PANEL | CR-315DAB MPB | 1 | 27123606 | <DAB MPB> |
| EV | A102 | HOLDER | KGLS-6RT | 6 | 27190693A | |
| EV | A103 | SCREW | 3TTB+8B(3BC) | 14 | 838430088GR | <MPP> |
| EV | A103 | SCREW | 3TTB+8B(3BC) | 15 | 838430088GR | <MDC> |
| EV | A103 | SCREW | 3TTB+8B(3BC) | 14 | 838430088GR | <MGT> |
| EV | A103 | SCREW | 3TTB+8B(3BC) | 14 | 838430088GR | <MDT> |
| EV | A103 | SCREW | 3TTB+8B(3BC) | 14 | 838430088GR | <MGQ> |
| EV | A103 | SCREW | 3TTB+8B(3BC) | 14 | 838430088GR | <DAB MPB> |
| EV | A105 | HOLDER | KGPS-6RF | 3 | 27191112 | |
| EV | A105 | NUT | --- | 1 | 800562 | <DAB MPB> |
| EV | A106 | HOLDER | KGLS-12RT | 3 | 27190266 | |
| EV | A107 | HOLDER | (PWB) | 1 | 27191280A | |
| EV | A107 | WASHER | --- | 1 | 870191 | <DAB MPB> |
| EV | A109 | COVER | (HT) | 1 | 28184981A | |
| EV | A110 | SCREW | 3TTB+8B(3BC) | 2 | 838430088GR | |
| EV | A112 | SCREW | 3TTB+8B(CU)SR | 4 | 801618 | |
| EV | A113 | HEAT SINK | 173 | 1 | 27160513-1 | |
| EV | A115 | SCREW | 3SMS8W.SW+14B(CU) | 4 | 801634 | |
| EV | A117 | SCREW | 3TTB+8B(CU)SR | 4 | 801618 | |
| EV | A119 | LEG | (AS) | 2 | 27175253-1B | |
| EV | A121 | SCREW | 3TTB+8B(3BC) | 2 | 838430088GR | |
| EV | A123 | SCREW | 4TTC+6C(3BC) | 4 | 830440069GR | |
| EV | A125 | TAPE | TAPE(CLOTH-16U) | (1) | 29110083 | |
| EV | A126 | SHLD PLT | (AMP) | 1 | 27150510 | |
| EV | A127 | SHLD PLT | (SP) | 1 | 27150511 | |
| EV | A128 | ISO PLT | (ST) | 1 | 28175326 | |

www.audiodna.sk

| | | | | | | |
|---|---|---|---|---|---|---|
| EV | A129 | WIRE TIE | BSK-1 | 4 | 260208 | |
| EV | A130 | IB CUSHION | W15 x 3t TAPE | 1 | 28141585 | |
| EV | A134 | RIVET | P-RIVET NRP-345 | 1 | 880009 | |
| EV | A200 | FACET | (S) | 1 | 28198906 | |
| EV | A201 | RIVET | P-RIVET NRP-345 | 4 | 880009 | <MPP> |
| EV | A201 | RIVET | P-RIVET NRP-345 | 4 | 880009 | <MGT> |
| EV | A201 | RIVET | P-RIVET NRP-345 | 4 | 880009 | <MGQ> |
| EV | A201 | RIVET | P-RIVET NRP-345 | 4 | 880009 | <DAB MPB> |
| EV | A206 | CLEAR PLT | --- | 1 | 28192105 | |
| EV | A209 | SCREW | 3TTB+6B(3BC) | 2 | 838430068GR | |
| EV | A212 | DOOR | (CD) | 1 | 28148656 | (B) |
| EV | A212 | DOOR | (CD) | 1 | 28148655 | (S) |
| EV | A215 | KNOB | (VOL)AS | 1 | 28326492 | (B) |
| EV | A215 | KNOB | (VOL)AS | 1 | 28326491 | (S) |
| EV | A301 | COVER | CR-315(B) | 1 | 28184976 | (B) |
| EV | A301 | COVER | CR-315(S) | 1 | 28184977 | (S) |
| EV | A302 | CUSHION | t5 x 30 x 5 | 1 | 28141562 | |
| EV | A303 | SCREW | 3TTB+8B(3BC) | 9 | 838430088GR | (B) |
| EV | A303 | SCREW | 3TTB+8B(3CM) | 9 | 838130088GR | (S) |
| EV | A305 | LABEL | RG-309250-1 | 1 | 29362285 | |
| EV | A307 | CUSHION | t5 x 30 x 5 | 1 | 28141562 | <DAB MPB> |
| EV | A309 | CUSHION | --- | 2 | 28141649 | |
| EV | A350 | F PANEL | (B) | 1 | 27212940 | (B) <MPP> |
| EV | A350 | F PANEL | (S)MPP | 1 | 27212942 | (S) <MPP> |
| EV | A350 | F PANEL | (S) | 1 | 27212939 | (S) <MDC> |
| EV | A350 | F PANEL | (S) | 1 | 27212939 | (S) <MGT> |
| EV | A350 | F PANEL | (S) | 1 | 27212939 | (S) <MDT> |
| EV | A350 | F PANEL | (S) | 1 | 27212939 | (S) <MGQ> |
| EV | A350 | F PANEL | DAB(S) | 1 | 27212941 | (S) <DAB MPB> |
| EV | A353 | LABEL | (UK-CR) | 1 | 29364600 | <DAB MPB> |
| EV | A501 | SPEC LABEL | CR-315 MPP | 1 | 29364494 | <MPP> |
| EV | A501 | SPEC LABEL | CR-315 MDC | 1 | 29364495 | <MDC> |
| EV | A501 | SPEC LABEL | CR-315 <MGT> | 1 | 29364496 | <MGT> |
| EV | A501 | SPEC LABEL | CR-315 MDT | 1 | 29364497 | <MDT> |
| EV | A501 | SPEC LABEL | CR-315 <MGT> | 1 | 29364496 | <MGQ> |
| EV | A501 | SPEC LABEL | CR-315DAB MPB | 1 | 29364498 | <DAB MPB> |
| EV | E002 | HOLDER | (CRAMP) UA-0 V0 | 1 | 27190608-1 | |
| EV | F901 | FUSE | 0.5A-SE-EAWK | 1 | 252063GR | !, <MPP> |
| EV | F901 | FUSE | 1.25A-T/UL-ST2 | 1 | 252251GR | !, <MDC> |
| EV | F901 | FUSE | 0.5A-SE-EAWK | 1 | 252063GR | !, <MGT> |
| EV | F901 | FUSE | 1.25A-T/UL-ST2 | 1 | 252251GR | !, <MDT> |
| EV | F901 | FUSE | 0.5A-SE-EAWK | 1 | 252063GR | !, <MGQ> |
| EV | F901 | FUSE | 0.5A-SE-EAWK | 1 | 252063GR | !, <DAB MPB> |
| EV | P1001 | SOCKET AS | NSAS-10P0997 | 1 | 20022391010 | |
| EV | P1002 | FFC | NCFC4-16045 | 1 | 204416045 | |
| EV | P1003 | SOCKET AS | NSAS-12P0960 | 1 | 20022391210UL | |
| EV | P1101 | FFC | NCFC7-130512 | 1 | 2047130512 | <MPP> |
| EV | P1101 | FFC | NCFC7-130512 | 1 | 2047130512 | <MDC> |
| EV | P1101 | FFC | NCFC7-130512 | 1 | 2047130512 | <MGT> |
| EV | P1101 | FFC | NCFC7-130512 | 1 | 2047130512 | <MDT> |
| EV | P1101 | FFC | NCFC7-130512 | 1 | 2047130512 | <MGQ> |
| EV | P1101 | FFC | NCFC3-13025 | 1 | 204313025 | <DAB MPB> |
| EV | P1102 | FFC | NCFC5-181012 | 1 | 2045181012 | |
| EV | Q557 | TR | 2SC3851-O | 1 | 2203383 | ! |
| EV | Q557 or | TR | 2SC3851-Y | (1) | 2203384 | ! |
| EV | Q557 or | TR | 2SD1267-Q | (1) | 2204052 | ! |

| | | | | | | |
|---|---|---|---|---|---|---|
| EV | Q557 or | TR | 2SD1267-P | (1) | 2204053 | ! |
| EV | Q558 | TR | 2SC3851-O | 1 | 2203383 | ! |
| EV | Q558 or | TR | 2SC3851-Y | (1) | 2203384 | ! |
| EV | Q558 or | TR | 2SD1267-Q | (1) | 2204052 | ! |
| EV | Q558 or | TR | 2SD1267-P | (1) | 2204053 | ! |
| EV | Q559 | TR | 2SA1488-O | 1 | 2203393 | ! |
| EV | Q559 or | TR | 2SA1488-Y | (1) | 2203394 | ! |
| EV | Q559 or | TR | 2SB942-Q | (1) | 2204042 | ! |
| EV | Q559 or | TR | 2SB942-P | (1) | 2204043 | ! |
| EV | Q560 | TR | 2SA1488-O | 1 | 2203393 | ! |
| EV | Q560 or | TR | 2SA1488-Y | (1) | 2203394 | ! |
| EV | Q560 or | TR | 2SB942-Q | (1) | 2204042 | ! |
| EV | Q560 or | TR | 2SB942-P | (1) | 2204043 | ! |
| EV | **<Note>** | | | | | |
| EV | Must use the same HFE rank mutually about the following parts. | | | | | |
| EV | Ref. No. : Q557 - Q559, Q558 - Q560 | | | | | |
| EV | T901 | P TRANS | NPT-1545P | 1 | 2301874 | !, <MPP> |
| EV | T901 | P TRANS | NPT-1545D | 1 | 2301873 | !, <MDC> |
| EV | T901 | P TRANS | NPT-1545P | 1 | 2301874 | !, <MGT> |
| EV | T901 | P TRANS | NPT-1545D | 1 | 2301873 | !, <MDT> |
| EV | T901 | P TRANS | NPT-1545P | 1 | 2301874 | !, <MGQ> |
| EV | T901 | P TRANS | NPT-1545P | 1 | 2301874 | !, <DAB MPB> |
| EV | U01 | PRE-AMP. MICROPROCESSOR PC board ass'y | NAAR-8931-1A | 1 | 1B147531-1A | <MPP> |
| EV | U01 | PRE-AMP. MICROPROCESSOR PC board ass'y | NAAR-8931-1B | 1 | 1B147531-1B | <MDC> |
| EV | U01 | PRE-AMP. MICROPROCESSOR PC board ass'y | NAAR-8931-1C | 1 | 1B147531-1C | <MGT> |
| EV | U01 | PRE-AMP. MICROPROCESSOR PC board ass'y | NAAR-8931-1E | 1 | 1B147531-1E | <MDT> |
| EV | U01 | PRE-AMP. MICROPROCESSOR PC board ass'y | NAAR-8931-1D | 1 | 1B147531-1D | <MGQ> |
| EV | U01 | PRE-AMP. MICROPROCESSOR PC board ass'y | NAAR-8931-1F | 1 | 1B147531-1F | <DAB MPB> |
| EV | U02 | CD PC board ass'y | NADG-8932-1A | 1 | 1B147532-1A | <MPP> |
| EV | U02 | CD PC board ass'y | NADG-8932-1B | 1 | 1B147532-1B | <MDC> |
| EV | U02 | CD PC board ass'y | NADG-8932-1C | 1 | 1B147532-1C | <MGT> |
| EV | U02 | CD PC board ass'y | NADG-8932-1E | 1 | 1B147532-1E | <MDT> |
| EV | U02 | CD PC board ass'y | NADG-8932-1D | 1 | 1B147532-1D | <MGQ. |
| EV | U02 | CD PC board ass'y | NADG-8932-1F | 1 | 1B147532-1F | <DAB MPB> |
| EV | U04 | DAB TERMINAL PC board ass'y | NAETC-8934-1F | 1 | 1B147534-1F | <DAB MPB> |
| EV | U05 | DISPLAY PC board ass'y | NADIS-8935-1A | 1 | 1B147535-1A | <MPP> |
| EV | U05 | DISPLAY PC board ass'y | NADIS-8935-1B | 1 | 1B147535-1B | <MDC> |
| EV | U05 | DISPLAY PC board ass'y | NADIS-8935-1C | 1 | 1B147535-1C | <MGT> |
| EV | U05 | DISPLAY PC board ass'y | NADIS-8935-1E | 1 | 1B147535-1E | <MDT> |
| EV | U05 | DISPLAY PC board ass'y | NADIS-8935-1D | 1 | 1B147535-1D | <MGQ> |
| EV | U05 | DISPLAY PC board ass'y | NADIS-8935-1F | 1 | 1B147535-1F | <DAB MPB> |
| EV | U06 | POWER AMPLIFIER PC board ass'y | NAAF-8936-1A | 1 | 1B147536-1A | <MPP> |
| EV | U06 | POWER AMPLIFIER PC board ass'y | NAAF-8936-1B | 1 | 1B147536-1B | <MDC> |
| EV | U06 | POWER AMPLIFIER PC board ass'y | NAAF-8936-1C | 1 | 1B147536-1C | <MGT> |
| EV | U06 | POWER AMPLIFIER PC board ass'y | NAAF-8936-1E | 1 | 1B147536-1E | <MDT> |
| EV | U06 | POWER AMPLIFIER PC board ass'y | NAAF-8936-1D | 1 | 1B147536-1D | <MGQ> |
| EV | U06 | POWER AMPLIFIER PC board ass'y | NAAF-8936-1F | 1 | 1B147536-1F | <DAB MPB> |
| EV | U07 | POWER SUPPLY PC board ass'y | NAPS-9837-1A | 1 | 1B147537-1A | <MPP> |
| EV | U07 | POWER SUPPLY PC board ass'y | NAPS-9837-1B | 1 | 1B147537-1B | <MDC> |
| EV | U07 | POWER SUPPLY PC board ass'y | NAPS-9837-1C | 1 | 1B147537-1C | <MGT> |
| EV | U07 | POWER SUPPLY PC board ass'y | NAPS-9837-1E | 1 | 1B147537-1E | <MDT> |
| EV | U07 | POWER SUPPLY PC board ass'y | NAPS-9837-1D | 1 | 1B147537-1D | <MGQ> |
| EV | U07 | POWER SUPPLY PC board ass'y | NAPS-9837-1F | 1 | 1B147537-1F | <DAB MPB> |
| EV | U08 | SPEAKER TERMINAL PC board ass'y | NAETC-8938-1B | 1 | --- | NSP, <MDC> |
| EV | U09 | SPEAKER TERMINAL PC board ass'y | NAETC-8939-1A | 1 | --- | NSP, <MPP> |
| EV | U09 | SPEAKER TERMINAL PC board ass'y | NAETC-8939-1C | 1 | --- | NSP, <MGT> |

| | | | | | | |
|---|---|---|---|---|---|---|
| EV | U09 | SPEAKER TERMINAL PC board ass'y | NAETC-8939-1E | 1 | --- | NSP, <MDT> |
| EV | U09 | SPEAKER TERMINAL PC board ass'y | NAETC-8939-1D | 1 | --- | NSP, <MGQ> |
| EV | U09 | SPEAKER TERMINAL PC board ass'y | NAETC-8939-1F | 1 | --- | NSP, <DAB MPB> |
| EV | U10 | TUNER UNIT | FAE485-E11EU | 1 | 240154 | <MPP> |
| EV | U10 | TUNER UNIT | ENG06507QFUS | 1 | 240156 | <MDC> |
| EV | U10 | TUNER UNIT | FAE485-E12EX | 1 | 240155 | <MGT> |
| EV | U10 | TUNER UNIT | FAE485-E12EX | 1 | 240155 | <MDT> |
| EV | U10 | TUNER UNIT | ENG07506QFEX | 1 | 240159 | <MGQ> |
| EV | U10 or | TUNER UNIT | FAE485-E12EX | (1) | 240155 | <MGQ> |
| EV | U10 | TUNER UNIT | FAE485-E11EU | 1 | 240154 | <DAB MPB> |
| EV | U11 | DAB MODULE | VENICE3.0-C-F | 1 | 24150071 | <DAB MPB> |

**CR-315/315DAB**

## EXPLODED VIEW PARTS LIST OF MECHANISM

### CD MECHANISM : DLM1A01-14CA / KSM-213CLCM

| | REF. NO. | PART NAME | DESCRIPTION | Q'TY | PART NO. | REMARKS |
|---|---|---|---|---|---|---|
| CD1 | Z005 | CD Tray loading unit | DLM1A01-14CA | 1 | 24800056 | |
| CD1 | Z006 | CD Drive unit | KSM-213CLCM | 1 | 24800017 | |
| CD1 | Z007 | INSULATOR | (CDC-A) | 4 | 24818058 | |
| CD1 | Z008 | SPRING | TP-D (silver) | 2 | 24820071 | |
| CD1 | Z009 | SPRING | TP-E (gold) | 2 | 24820072 | |
| CD1 | Z010 | SCREW | 2.6 x 8 x w10 | 4 | 801632 | |

### CD TRAY LOADING UNIT : DLM1A01-14CA

| | REF. NO. | PART NAME | DESCRIPTION | Q'TY | PART NO. | REMARKS |
|---|---|---|---|---|---|---|
| CD2 | 1 | CHASSIS | --- | 1 | 65-210-1054 | |
| CD2 | 2 | TRAY | --- | 1 | 65-218-1055 | |
| CD2 | 3 | SUB CHASSIS | --- | 1 | 65-211-2040 | |
| CD2 | 4 | CAM SLIDER | --- | 1 | 65-239-2004 | |
| CD2 | 5 | GEAR TRAY | --- | 1 | 65-222-3005 | |
| CD2 | 6 | CLAMPER ASS'Y | --- | 1 | 65-093-4057H | |
| CD2 | 7 | PWB ASS'Y | --- | 1 | 65-093-4058H | |
| CD2 | 8 | GEAR A | --- | 1 | 65-222-4037 | |
| CD2 | 9 | PULLEY GEAR | --- | 1 | 65-222-4004 | |
| CD2 | 10 | MOTOR ASS'Y | --- | 1 | 65-093-4068H | |
| CD2 | 11 | LOADING BELT | --- | 1 | 02-083-4274 | |
| CD2 | 12 | SCREW | --- | 2 | GSP14A25027 | |

### CD DRIVE UNIT : KSM-213CLCM

| | REF. NO. | PART NAME | DESCRIPTION | Q'TY | PART NO. | REMARKS |
|---|---|---|---|---|---|---|
| CD3 | 51 | Motor chassis ass'y | --- | 1 | X-2656-877-1 | |
| CD3 | 52 | Motor gear ass'y | --- | 1 | X2625-769-1 | |
| CD3 | 53 | Sled shaft | --- | 1 | 2626-908-01 | |
| CD3 | 54 | Gear (A) (S) | --- | 1 | 24810023 | |
| CD3 | 55 | P2 x 3, Screw | --- | 2 | 7621-255-15 | |
| CD3 | 56 | Leaf switch | --- | 1 | 24840008 | |
| CD3 | 57 | Motor PC board | --- | 1 | 1639-678-12 | |
| CD3 | 58 | Connector 6pin | --- | 1 | 1-564-722-11 | |
| CD3 | 61 | KSS-213C, Pickup | --- | 1 | 8848-483-05 | |

**CR-315/315DAB**

## PC BOARD PARTS LIST

**U01** PRE-AMP. & MICROPROCESSOR PC BOARD (NAAR-8931-1A / 1B / 1C / 1D / 1E / 1F)
**U02** CD PC BOARD (NADG-8932-1A / 1B / 1C / 1D / 1E / 1F)
**U04** DAB TERMINAL PC BOARD (NAETC-8934-1B)

www.audiodna.sk

<Note> U04 : DAB MPB Only

| | CIRCUIT NO. | PART NAME | DESCRIPTION | Q'TY | PART NO. (SN) | REMARKS |
|---|---|---|---|---|---|---|
| PCB1 | Q101 | IC | MPD784225GC-305-8BT-A | 1 | 22242295R3 | |
| PCB1 | Q102 | IC | TC74VHC541FT | 1 | 22274541ER2TO | |
| PCB1 | Q201 | IC | BD7931F | 1 | 22242216R2 | |
| PCB1 | Q202 | IC | BA5947FP | 1 | 22242215R2 | |
| PCB1 | Q204 | IC | PQ033ENA1ZPH | 1 | 22242334R2 | |
| PCB1 | Q206 | IC | CXD3014AR | 1 | 22242264R3 | |
| PCB1 | Q207 | IC | MPD120N18T1B-E1-AZ | 1 | 22278018NR2NE | |
| PCB1 | Q401 | IC | R2S15211FP | 1 | 22242297R3 | |
| PCB1 | Q707 | IC | S-24CS16A0I-J8V1G | 1 | 22242326R2 | |
| PCB1 | Q708 | IC | S-812C50AUA-C3E | 1 | 22242240R2 | |
| PCB1 | Q709 | IC | M30622MWP-B07FP | 1 | 22242377R3 | |
| PCB1 | Q710 | IC | S-80140CNMC-JKZ-T2 | 1 | 22242238R2 | |
| PCB1 | Q902 | IC | S-80140CNMC-JKZ-T2 | 1 | 22242238R2 | |
| PCB1 | Q904 | IC | MPC2906HF | 1 | 22278006DNE | |
| PCB1 | Q905 | IC | UPC2905AHF-AZ | 1 | 22278005DNE | <DAB MPB> |
| PCB1 | Q905 or | IC | MPC2905BHF | (1) | 22278005DBNE | <DAB MPB> |
| PCB1 | Q906 | IC | MPC2933AHF | 1 | 22278033DNE | <DAB MPB> |
| PCB1 | Q906 or | IC | MPC2933BHF-AZ | (1) | 22278033DBNE | <DAB MPB> |
| PCB1 | Q906A | HEAT-SINK | HEAT-SINK(RAD-68) | 1 | 27160211 | <DAB MPB> |
| PCB1 | Q906B | SCREW | 3P+10FN(3BC) | 1 | 82143010GR | <DAB MPB> |
| PCB1 | Q907 | IC | MPC2905AT | 1 | 22278005DR2NE | |
| PCB1 | Q907 or | IC | TA4805AF(TE16L_NQ) | (1) | 22278005DR2TO | |
| PCB1 | Q921 | IC | MPC2905AT | 1 | 22278005DR2NE | |
| PCB1 | Q921 or | IC | TA4805AF(TE16L_NQ) | (1) | 22278005DR2TO | |
| PCB1 | Q925 | IC | 78M08HF(NJM78M08FA) | 1 | 222780085JRC | |
| PCB1 | Q926 | IC | 79M08HF(NJM79M08FA) | 1 | 222790085JRC | |
| PCB1 | Q951 | IC | 78M09HF(NJM78M09FA) | 1 | 222780095JRC | |
| PCB1 | Q2209 | IC | NJM4580M-D | 1 | 22241448R2 | |
| PCB1 | Q208 | TR | 2SA1162-GR | 1 | 2214375R2 | |
| PCB1 | Q432 | TR | 2SC2712-GR | 1 | 2213145R2 | |
| PCB1 | Q433 | TR | 2SA1162-GR | 1 | 2214375R2 | |
| PCB1 | Q702 | TR | RN2403 | 1 | 2214540R2 | |
| PCB1 | Q703 | TR | RN2402 | 1 | 2214530R2 | |
| PCB1 | Q705 | TR | RN2403 | 1 | 2214540R2 | |
| PCB1 | Q706 | TR | RN2403 | 1 | 2214540R2 | |
| PCB1 | Q941 | TR | 2SA1015-GR | 1 | 2211455T | |
| PCB1 | Q2210 | TR | RN1441 | 1 | 2215410R2 | |
| PCB1 | Q2211 | TR | RN1441 | 1 | 2215410R2 | |
| PCB1 | Q7101 | TR | RN1401(TE85L_F) | 1 | 2214460R2 | <DAB MPB> |
| PCB1 | Q7102 | TR | RN2402 | 1 | 2214530R2 | <DAB MPB> |
| PCB1 | D101 | C-DIODE | 1SS355 | 1 | 223269R2 | |
| PCB1 | D101 or | C-DIODE | 1SS352 | (1) | 223234R2 | |
| PCB1 | D102 | C-DIODE | 1SS355 | 1 | 223269R2 | |
| PCB1 | D102 or | C-DIODE | 1SS352 | (1) | 223234R2 | |
| PCB1 | D201 | C-DIODE | 1SS355 | 1 | 223269R2 | |
| PCB1 | D201 or | C-DIODE | 1SS352 | (1) | 223234R2 | |
| PCB1 | D425 | C-DIODE | 1SS355 | 1 | 223269R2 | |
| PCB1 | D425 or | C-DIODE | 1SS352 | (1) | 223234R2 | |
| PCB1 | D701 | ZENER D | UDZS5.1B | 1 | 224550510R2 | |
| PCB1 | D702 | C-DIODE | 1SS355 | 1 | 223269R2 | |
| PCB1 | D702 or | C-DIODE | 1SS352 | (1) | 223234R2 | |
| PCB1 | D905 | C-DIODE | S1NB60-4062 | 1 | 22380318R2 | |
| PCB1 | D906 | DIODE | D5SBA20 | 1 | 22380130F | <MGT> |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB1 | D906 | DIODE | D5SBA20 | 1 | 22380130F | <MGQ> |
| PCB1 | D906 | DIODE | D5SBA20 | 1 | 22380130F | <DAB MPB> |
| PCB1 | D906A | DIODE | D3SBA20 | 1 | 22380271F | <MPP> |
| PCB1 | D906A | DIODE | D3SBA20 | 1 | 22380271F | <MDC> |
| PCB1 | D906A | DIODE | D3SBA20 | 1 | 22380271F | <MDT> |
| PCB1 | D907 | DIODE | RL1N4003 | 1 | 22380260T | |
| PCB1 | D907 or | DIODE | GP104003E | (1) | 22380035T | |
| PCB1 | D941 | DIODE | RL1N4003 | 1 | 22380260T | |
| PCB1 | D941 or | DIODE | GP104003E | (1) | 22380035T | |
| PCB1 | D943 | ZENER D | UDZS27B | 1 | 224552700R2 | |
| PCB1 | D951 | DIODE | RBV402 | 1 | 22380022F | |
| PCB1 | D951 or | DIODE | D3SBA20 | (1) | 22380271F | |
| PCB1 | X101 | CERA LOCK | CSTCE12M5G52-R0 | 1 | 3010361R2 | |
| PCB1 | X201 | CRYSTAL | FCX-03-16.9344MHz | 1 | 3010428R2 | |
| PCB1 | X701 | CERA LOCK | CSTCR6M0055-R0 | 1 | 3010397R2 | |
| PCB1 | X702 | CRYSTAL | DT-38 | 1 | 3010282 | |
| PCB1 | X702 or | CRYSTAL | VT-200-F | (1) | 3010436 | |
| PCB1 | L204 | CHOKE COIL | NCH-1471 | 1 | 231237K022R2 | |
| PCB1 | L601 | CHOKE COIL | NCH-1471 | 1 | 231237K022R2 | |
| PCB1 | L7901 | CHOKE COIL | BLM21B222SPT | 1 | 230921R2 | |
| PCB1 | C108 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C111 | C-CERA C | CK725F1H-473Z1 | 1 | 332154730R1 | |
| PCB1 | C112 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C113 | C-CERA C | CK725F1A-105Z1 | 1 | 332181050R1 | |
| PCB1 | C201 | C-CERA C | CK725B1H-472K1 | 1 | 332104725R1 | |
| PCB1 | C202 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C203 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C204 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C206 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C209 | ELECT C | CE04W6.3V-220M | 1 | 355722219T | |
| PCB1 | C210 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C211 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C212 | ELECT C | CE04W6.3V-100M | 1 | 355721019T | |
| PCB1 | C213 | ELECT C | CE04W6.3V-100M | 1 | 355721019T | |
| PCB1 | C214 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C215 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C220 | C-CERA C | CK725F1A-105Z1 | 1 | 332181050R1 | |
| PCB1 | C221 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C222 | C-CERA C | CK725F1A-105Z1 | 1 | 332181050R1 | |
| PCB1 | C223 | C-CERA C | CK725B1C-105K1 | 1 | 332121055R1 | |
| PCB1 | C231 | ELECT C | CE04W6.3V-220M | 1 | 355722219T | |
| PCB1 | C234 | C-CERA C | CC725CH1H-102J1 | 1 | 342101024R1 | |
| PCB1 | C235 | C-CERA C | CK725B1H-152K1 | 1 | 332101525R1 | |
| PCB1 | C236 | ELECT C | CE04W6.3V-220M | 1 | 355722219T | |
| PCB1 | C238 | C-CERA C | CK725F1A-105Z1 | 1 | 332181050R1 | |
| PCB1 | C240 | C-CERA C | CK725B1H-332K1 | 1 | 332103325R1 | |
| PCB1 | C241 | C-CERA C | CK725B1C-104K1 | 1 | 332121045R1 | |
| PCB1 | C242 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C243 | C-CERA C | CK725B1H-103K1 | 1 | 332101035R1 | |
| PCB1 | C244 | C-CERA C | CK725B1C-104K1 | 1 | 332121045R1 | |
| PCB1 | C245 | C-CERA C | CK725B1C-104K1 | 1 | 332121045R1 | |
| PCB1 | C246 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C248 | ELECT C | CE04W6.3V-220M | 1 | 355722219T | |
| PCB1 | C250 | C-CERA C | CK725B1A-474K1 | 1 | 332134745R1 | |
| PCB1 | C251 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C252 | C-CERA C | CK725B1C-104K1 | 1 | 332121045R1 | |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB1 | C253 | C-CERA C | CK725B1H-152K1 | 1 | 332101525R1 | |
| PCB1 | C256 | ELECT C | CE04W6.3V-220M | 1 | 355722219T | |
| PCB1 | C257 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C258 | ELECT C | CE04W6.3V-100M | 1 | 355721019T | |
| PCB1 | C259 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C260 | ELECT C | CE04W6.3V-100M | 1 | 355721019T | |
| PCB1 | C264 | C-CERA C | CC725CH1H-102J1 | 1 | 342101024R1 | |
| PCB1 | C265 | C-CERA C | CC725CH1H-180J1 | 1 | 342101804R1 | |
| PCB1 | C266 | C-CERA C | CC725CH1H-180J1 | 1 | 342101804R1 | |
| PCB1 | C267 | C-CERA C | CK725F1A-105Z1 | 1 | 332181050R1 | |
| PCB1 | C269 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C270 | VX C | CE04W16V-470M(VX_BLK) | 1 | 397344717T | |
| PCB1 | C271 | VX C | CE04W16V-470M(VX_BLK) | 1 | 397344717T | |
| PCB1 | C272 | C-CERA C | CK725B1C-104K1 | 1 | 332121045R1 | |
| PCB1 | C400 | C-CERA C | CC725CH1H-221J1 | 1 | 342102214R1 | |
| PCB1 | C401 | C-CERA C | CC725CH1H-221J1 | 1 | 342102214R1 | |
| PCB1 | C404 | C-CERA C | CC725CH1H-221J1 | 1 | 342102214R1 | |
| PCB1 | C405 | C-CERA C | CC725CH1H-221J1 | 1 | 342102214R1 | |
| PCB1 | C412 | TF C | ECQ-V50V-474J | 1 | 374724744T | |
| PCB1 | C413 | TF C | ECQ-V50V-474J | 1 | 374724744T | |
| PCB1 | C414 | TF C | ECQ-V50V-473J | 1 | 374724734T | |
| PCB1 | C415 | TF C | ECQ-V50V-473J | 1 | 374724734T | |
| PCB1 | C416 | TF C | ECQ-B50V-223J | 1 | 374722234T | |
| PCB1 | C417 | TF C | ECQ-B50V-223J | 1 | 374722234T | |
| PCB1 | C418 | VX C | CE04W50V 47M(VX_BLK) | 1 | 397384707T | |
| PCB1 | C419 | VX C | CE04W50V 47M(VX_BLK) | 1 | 397384707T | |
| PCB1 | C422 | C-CERA C | CK725B1C-104K1 | 1 | 332121045R1 | |
| PCB1 | C437 | VX C | CE04W50V-22M(VX_BLK) | 1 | 397382207T | |
| PCB1 | C438 | VX C | CE04W50V-22M(VX_BLK) | 1 | 397382207T | |
| PCB1 | C441 | ELECT C | CE04W50V-3.3M | 1 | 355780339T | |
| PCB1 | C442 | VX C | CE04W10V-100M(VX_BLK) | 1 | 397331017T | |
| PCB1 | C602 | ELECT C | CE04W50V-3.3M | 1 | 355780339T | |
| PCB1 | C605 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C606 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C607 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | |
| PCB1 | C608 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | |
| PCB1 | C609 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | |
| PCB1 | C610 | ELECT C | CE04W50V-3.3M | 1 | 355780339T | |
| PCB1 | C611 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | |
| PCB1 | C701 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C702 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C703 | ELECT C | CE04W6.3V-220M | 1 | 355722219T | |
| PCB1 | C704 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C706 | C-CERA C | CK725F1A-105Z1 | 1 | 332181050R1 | |
| PCB1 | C707 | C-CERA C | CK725F1A-105Z1 | 1 | 332181050R1 | |
| PCB1 | C708 | C-CERA C | CK725F1A-105Z1 | 1 | 332181050R1 | |
| PCB1 | C712 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | |
| PCB1 | C713 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C714 | C-CERA C | CC725CH1H-102J1 | 1 | 342101024R1 | |
| PCB1 | C715 | C-CERA C | CC725CH1H-270J1 | 1 | 342102704R1 | |
| PCB1 | C716 | TRIM C | NTC-45P27 | 1 | 3060031 | |
| PCB1 | C717 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | |
| PCB1 | C719 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C720 | TF C | ECQ-V50V-334J | 1 | 374723344T | |
| PCB1 | C7901 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | C905 | VX C | CE04W6.3V-470M(VX_BLK) | 1 | 397324717T | |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB1 | C910 | VX C | CE04W16V-1000M(VX_BLK) | 1 | 397341027S | |
| PCB1 | C911 | VX C | CE04W16V-2200M(VX_BLK) | 1 | 397342227S | |
| PCB1 | C912 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C916 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C917 | VX C | CE04W25V-220M(VX_BLK) | 1 | 397352217T | |
| PCB1 | C918 | C-CERA C | CK725F1H-224Z1 | 1 | 332152240R1 | |
| PCB1 | C919 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C921 | C-CERA C | CK725F1A-105Z1 | 1 | 332181050R1 | |
| PCB1 | C922 | VX C | CE04W16V-470M(VX_BLK) | 1 | 397344717T | |
| PCB1 | C925 | VX C | CE04W25V-3300M(VX_BLK) | 1 | 397353327S | <MPP> |
| PCB1 | C925 | VX C | CE04W25V-1000M(VX_BLK) | 1 | 397351027S | <MDC> |
| PCB1 | C925 | VX C | CE04W25V-3300M(VX_BLK) | 1 | 397353327S | <MGT> |
| PCB1 | C925 | VX C | CE04W25V-3300M(VX_BLK) | 1 | 397353327S | <MDT> |
| PCB1 | C925 | VX C | CE04W25V-3300M(VX_BLK) | 1 | 397353327S | <MGQ> |
| PCB1 | C925 | VX C | CE04W25V-3300M(VX_BLK) | 1 | 397353327S | <DAB MPB> |
| PCB1 | C926 | VX C | CE04W25V-1000M(VX_BLK) | 1 | 397351027S | <MPP> |
| PCB1 | C926 | VX C | CE04W25V-470M(VX_BLK) | 1 | 397354717T | <MDC> |
| PCB1 | C926 | VX C | CE04W25V-1000M(VX_BLK) | 1 | 397351027S | <MGT> |
| PCB1 | C926 | VX C | CE04W25V-1000M(VX_BLK) | 1 | 397351027S | <MDT> |
| PCB1 | C926 | VX C | CE04W25V-1000M(VX_BLK) | 1 | 397351027S | <MGQ> |
| PCB1 | C926 | VX C | CE04W25V-1000M(VX_BLK) | 1 | 397351027S | <DAB MPB> |
| PCB1 | C927 | VX C | CE04W25V-220M(VX_BLK) | 1 | 397352217T | |
| PCB1 | C928 | VX C | CE04W25V-220M(VX_BLK) | 1 | 397352217T | |
| PCB1 | C929 | VX C | CE04W16V-470M(VX_BLK) | 1 | 397344717T | |
| PCB1 | C930 | VX C | CE04W16V-470M(VX_BLK) | 1 | 397344717T | |
| PCB1 | C941 | TF C | ECQ-V50V-104J | 1 | 374721044T | |
| PCB1 | C942 | VX C | CE04W50V-220M(VX_BLK) | 1 | 397382217S | |
| PCB1 | C943 | C-CERA C | CK725F1H-223Z1 | 1 | 332152230R1 | |
| PCB1 | C944 | TF C | ECQ-V50V-473J | 1 | 374724734T | |
| PCB1 | C945 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | <DAB MPB> |
| PCB1 | C946 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | <DAB MPB> |
| PCB1 | C947 | VX C | CE04W6.3V-470M(VX_BLK) | 1 | 397324717T | <DAB MPB> |
| PCB1 | C948 | VX C | CE04W10V-220M(VX_BLK) | 1 | 397332217T | <DAB MPB> |
| PCB1 | C951 | TF C | ECQ-V50V-334J | 1 | 374723344T | |
| PCB1 | C952 | TF C | ECQ-V50V-334J | 1 | 374723344T | |
| PCB1 | C955 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB1 | C956 | VX C | CE04W50V 100M(VX_BLK) | 1 | 397381017T | |
| PCB1 | C957 | VX C | CE04W25V-220M(VX_BLK) | 1 | 397352217T | |
| PCB1 | C958 | TF C | ECQ-B50V-223J | 1 | 374722234T | |
| PCB1 | C2216 | C-CERA C | CK725B1H-222K1 | 1 | 332102225R1 | |
| PCB1 | C2217 | C-CERA C | CK725B1H-222K1 | 1 | 332102225R1 | |
| PCB1 | C2218 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MDC> |
| PCB1 | C2218 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MGT> |
| PCB1 | C2218 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MDT> |
| PCB1 | C2218 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MGQ> |
| PCB1 | C2218 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <DAB MPB> |
| PCB1 | C2219 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MDC> |
| PCB1 | C2219 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MGT> |
| PCB1 | C2219 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MDT> |
| PCB1 | C2219 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MGQ> |
| PCB1 | C2219 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <DAB MPB> |
| PCB1 | C2220 | VX C | CE04W25V-47M(VX_BLK) | 1 | 397354707T | |
| PCB1 | C2221 | VX C | CE04W25V-47M(VX_BLK) | 1 | 397354707T | |
| PCB1 | C2222 | TF C | ECQ-B50V-561J | 1 | 374725614T | |
| PCB1 | C2223 | TF C | ECQ-B50V-561J | 1 | 374725614T | |
| PCB1 | C2224 | TF C | ECQ-B50V-102J | 1 | 374721024T | |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB1 | C2225 | TF C | ECQ-B50V-102J | 1 | 374721024T | |
| PCB1 | C2226 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MDC> |
| PCB1 | C2226 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MGT> |
| PCB1 | C2226 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MDT> |
| PCB1 | C2226 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MGQ> |
| PCB1 | C2226 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <DAB MPB> |
| PCB1 | C2227 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MDC> |
| PCB1 | C2227 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MGT> |
| PCB1 | C2227 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MDT> |
| PCB1 | C2227 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <MGQ> |
| PCB1 | C2227 | C-CERA C | CC725CH1H-101J1 | 1 | 342101014R1 | <DAB MPB> |
| PCB1 | C2228 | VX C | CE04W50V 47M(VX_BLK) | 1 | 397384707T | |
| PCB1 | C2229 | VX C | CE04W50V 47M(VX_BLK) | 1 | 397384707T | |
| PCB1 | C2230 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | <MPP> |
| PCB1 | C2230 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | <MGT> |
| PCB1 | C2230 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | <MDT> |
| PCB1 | C2230 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | <MGQ> |
| PCB1 | C2230 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | <DAB MPB> |
| PCB1 | C2231 | VX C | CE04W25V-220M(VX_BLK) | 1 | 397352217T | |
| PCB1 | C2232 | VX C | CE04W25V-220M(VX_BLK) | 1 | 397352217T | |
| PCB1 | C7144 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | <DAB MPB> |
| PCB1 | R007 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R008 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R101 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R102 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R103 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R105 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R106 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R107 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R108 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R109 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R110 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R111 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R112 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R113 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R114 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R115 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R116 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R117 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R118 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R119 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R121 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R122 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R123 | C-CARBON R | RN72K1J-470JE | 1 | 435034704R1 | |
| PCB1 | R124 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R125 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R126 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R128 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R129 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R130 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R131 | C-CARBON R | RN72K1J-220JE | 1 | 435032204R1 | |
| PCB1 | R132 | C-CARBON R | RN72K1J-220JE | 1 | 435032204R1 | |
| PCB1 | R133 | C-CARBON R | RN72K1J-220JE | 1 | 435032204R1 | |
| PCB1 | R134 | C-CARBON R | RN72K1J-220JE | 1 | 435032204R1 | |
| PCB1 | R135 | C-CARBON R | RN72K1J-220JE | 1 | 435032204R1 | |
| PCB1 | R136 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB1 | R137 | C-CARBON R | RN72K1J-561JE | 1 | 435035614R1 | |
| PCB1 | R138 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R139 | C-CARBON R | RN72K1J-470JE | 1 | 435034704R1 | |
| PCB1 | R142 | C-CARBON R | RN72K1J-470JE | 1 | 435034704R1 | |
| PCB1 | R144 | C-CARBON R | RN72K1J-470JE | 1 | 435034704R1 | |
| PCB1 | R145 | C-CARBON R | RN72K1J-470JE | 1 | 435034704R1 | |
| PCB1 | R146 | C-CARBON R | RN72K1J-470JE | 1 | 435034704R1 | |
| PCB1 | R148 | C-CARBON R | RN72K1J-561JE | 1 | 435035614R1 | |
| PCB1 | R149 | C-CARBON R | RN72K1J-391JE | 1 | 435033914R1 | |
| PCB1 | R150 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R151 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R152 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R153 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |
| PCB1 | R154 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |
| PCB1 | R155 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |
| PCB1 | R156 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R157 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R158 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R159 | C-CARBON R | RN72K1J-561JE | 1 | 435035614R1 | |
| PCB1 | R160 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R161 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R162 | C-CARBON R | RN72K1J-561JE | 1 | 435035614R1 | |
| PCB1 | R202 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R203 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R204 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R205 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R206 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R207 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R208 | C-CARBON R | RN72K1J-223JE | 1 | 435032234R1 | |
| PCB1 | R209 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R210 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R211 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R212 | C-CARBON R | RN72K1J-153JE | 1 | 435031534R1 | |
| PCB1 | R213 | C-CARBON R | RN72K1J-822JE | 1 | 435038224R1 | |
| PCB1 | R214 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R227 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R232 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R236 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R239 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R240 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R241 | C-CARBON R | RN72K1J-330JE | 1 | 435033304R1 | |
| PCB1 | R242 | C-CARBON R | RN72K1J-330JE | 1 | 435033304R1 | |
| PCB1 | R243 | C-CARBON R | RN72K1J-104JE | 1 | 435031044R1 | |
| PCB1 | R265 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R266 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |
| PCB1 | R268 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R274 | C-CARBON R | RN72K1J-221JE | 1 | 435032214R1 | |
| PCB1 | R275 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R277 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R278 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R279 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R280 | C-CARBON R | RN72K1J-153JE | 1 | 435031534R1 | |
| PCB1 | R281 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R282 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R283 | C-CARBON R | RN72K1J-472JE | 1 | 435034724R1 | |
| PCB1 | R284 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB1 | R285 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R286 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R287 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R288 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R289 | C-CARBON R | RN72K1J-472JE | 1 | 435034724R1 | |
| PCB1 | R290 | C-CARBON R | RN72K1J-474JE | 1 | 435034744R1 | |
| PCB1 | R291 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R292 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R293 | C-CARBON R | RN72K1J-104JE | 1 | 435031044R1 | |
| PCB1 | R294 | C-CARBON R | RN72K1J-105JE | 1 | 435031054R1 | |
| PCB1 | R295 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R297 | C-CARBON R | RN72K1J-332JE | 1 | 435033324R1 | |
| PCB1 | R298 | C-CARBON R | RN72K1J-223JE | 1 | 435032234R1 | |
| PCB1 | R400 | C-CARBON R | RN72K1J-331JE | 1 | 435033314R1 | |
| PCB1 | R401 | C-CARBON R | RN72K1J-331JE | 1 | 435033314R1 | |
| PCB1 | R402 | C-CARBON R | RN72K1J-563JE | 1 | 435035634R1 | |
| PCB1 | R403 | C-CARBON R | RN72K1J-563JE | 1 | 435035634R1 | |
| PCB1 | R404 | C-CARBON R | RN72K1J-222JE | 1 | 435032224R1 | |
| PCB1 | R405 | C-CARBON R | RN72K1J-222JE | 1 | 435032224R1 | |
| PCB1 | R406 | C-CARBON R | RN72K1J-224JE | 1 | 435032244R1 | |
| PCB1 | R407 | C-CARBON R | RN72K1J-224JE | 1 | 435032244R1 | |
| PCB1 | R408 | C-CARBON R | RN72K1J-331JE | 1 | 435033314R1 | |
| PCB1 | R409 | C-CARBON R | RN72K1J-331JE | 1 | 435033314R1 | |
| PCB1 | R410 | C-CARBON R | RN72K1J-563JE | 1 | 435035634R1 | |
| PCB1 | R411 | C-CARBON R | RN72K1J-563JE | 1 | 435035634R1 | |
| PCB1 | R421 | C-CARBON R | RN72K1J-222JE | 1 | 435032224R1 | |
| PCB1 | R422 | C-CARBON R | RN72K1J-222JE | 1 | 435032224R1 | |
| PCB1 | R423 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R424 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R4252 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R426 | C-CARBON R | RN72K1J-105JE | 1 | 435031054R1 | |
| PCB1 | R427 | C-CARBON R | RN72K1J-105JE | 1 | 435031054R1 | |
| PCB1 | R430 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R431 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R447 | C-CARBON R | RN72K1J-222JE | 1 | 435032224R1 | |
| PCB1 | R448 | C-CARBON R | RN72K1J-222JE | 1 | 435032224R1 | |
| PCB1 | R449 | C-CARBON R | RN72K1J-104JE | 1 | 435031044R1 | |
| PCB1 | R450 | C-CARBON R | RN72K1J-104JE | 1 | 435031044R1 | |
| PCB1 | R451 | C-CARBON R | RN72K1J-224JE | 1 | 435032244R1 | |
| PCB1 | R452 | C-CARBON R | RN72K1J-222JE | 1 | 435032224R1 | |
| PCB1 | R453 | C-CARBON R | RN72K1J-393JE | 1 | 435033934R1 | |
| PCB1 | R454 | C-CARBON R | RN72K1J-123JE | 1 | 435031234R1 | |
| PCB1 | R455 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R456 | C-CARBON R | RN72K1J-223JE | 1 | 435032234R1 | |
| PCB1 | R601 | C-CARBON R | RN72K1J-222JE | 1 | 435032224R1 | |
| PCB1 | R602 | C-CARBON R | RN72K1J-222JE | 1 | 435032224R1 | |
| PCB1 | R603 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R604 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R605 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R606 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R607 | C-CARBON R | RN72K1J-273JE | 1 | 435032734R1 | |
| PCB1 | R608 | C-CARBON R | RN72K1J-273JE | 1 | 435032734R1 | |
| PCB1 | R609 | C-CARBON R | RN72K1J-392JE | 1 | 435033924R1 | |
| PCB1 | R610 | C-CARBON R | RN72K1J-104JE | 1 | 435031044R1 | |
| PCB1 | R611 | C-CARBON R | RN72K1J-392JE | 1 | 435033924R1 | |
| PCB1 | R612 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB1 | R613 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | <MPP> |
| PCB1 | R613 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | <DAB MPB> |
| PCB1 | R614 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | <MPP> |
| PCB1 | R614 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | <DAB MPB> |
| PCB1 | R701 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R702 | C-CARBON R | RN72K1J-224JE | 1 | 435032244R1 | |
| PCB1 | R703 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R704 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R705 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R706 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R707 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R708 | C-CARBON R | RN72K1J-272JE | 1 | 435032724R1 | |
| PCB1 | R709 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MPP> |
| PCB1 | R709 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <DAB MPB> |
| PCB1 | R710 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R711 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R712 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R713 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <DAB MPB> |
| PCB1 | R714 | C-CARBON R | RN72K1J-272JE | 1 | 435032724R1 | |
| PCB1 | R715 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R716 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R717 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R718 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R719 | C-CARBON R | RN72K1J-272JE | 1 | 435032724R1 | |
| PCB1 | R720 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R721 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R722 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R723 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R724 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R725 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R726 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MPP> |
| PCB1 | R726 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MDC> |
| PCB1 | R726 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MGT> |
| PCB1 | R726 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MDT> |
| PCB1 | R726 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MGQ> |
| PCB1 | R727 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R728 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MDC> |
| PCB1 | R728 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MGT> |
| PCB1 | R728 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MDT> |
| PCB1 | R728 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MGQ> |
| PCB1 | R729 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R730 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R731 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R732 | C-CARBON R | RN72K1J-220JE | 1 | 435032204R1 | |
| PCB1 | R733 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R734 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R735 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R736 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R737 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R738 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R739 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R740 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R741 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R742 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R743 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R744 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB1 | R745 | C-CARBON R | RN72K1J-561JE | 1 | 435035614R1 | |
| PCB1 | R746 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R747 | C-CARBON R | RN72K1J-561JE | 1 | 435035614R1 | |
| PCB1 | R748 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R750 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R751 | C-CARBON R | RN72K1J-561JE | 1 | 435035614R1 | |
| PCB1 | R753 | C-CARBON R | RN72K1J-561JE | 1 | 435035614R1 | |
| PCB1 | R756 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R757 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R758 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MPP> |
| PCB1 | R758 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | <MDC> |
| PCB1 | R758 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MGT> |
| PCB1 | R758 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MGQ> |
| PCB1 | R758 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MDT> |
| PCB1 | R758 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <DAB MPB> |
| PCB1 | R759 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R760 | C-CARBON R | RN72K1J-333JE | 1 | 435033334R1 | <MPP> |
| PCB1 | R760 | C-CARBON R | RN72K1J-333JE | 1 | 435033334R1 | <MGT> |
| PCB1 | R760 | C-CARBON R | RN72K1J-333JE | 1 | 435033334R1 | <MGQ> |
| PCB1 | R760 | C-CARBON R | RN72K1J-333JE | 1 | 435033334R1 | <MDT> |
| PCB1 | R760 | C-CARBON R | RN72K1J-333JE | 1 | 435033334R1 | <DAB MPB> |
| PCB1 | R761 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | <MPP> |
| PCB1 | R761 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | <MDC> |
| PCB1 | R761 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | <MGT> |
| PCB1 | R761 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | <MDT> |
| PCB1 | R761 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | <MGQ> |
| PCB1 | R761 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | <DAB MPB> |
| PCB1 | R763 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R764 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R765 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R766 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R767 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R768 | C-CARBON R | RN72K1J-272JE | 1 | 435032724R1 | |
| PCB1 | R769 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R770 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R771 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R772 | C-CARBON R | RN72K1J-470JE | 1 | 435034704R1 | |
| PCB1 | R773 | C-CARBON R | RN72K1J-272JE | 1 | 435032724R1 | |
| PCB1 | R774 | C-CARBON R | RN72K1J-470JE | 1 | 435034704R1 | |
| PCB1 | R775 | C-CARBON R | RN72K1J-470JE | 1 | 435034704R1 | |
| PCB1 | R776 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R777 | C-CARBON R | RN72K1J-470JE | 1 | 435034704R1 | |
| PCB1 | R778 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R779 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R780 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R781 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R782 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R783 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R784 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R785 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R786 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R787 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R788 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R789 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R790 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R7901 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB1 | R791 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R792 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R793 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R794 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R795 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R796 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB1 | R797 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R799 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB1 | R907 | METAL R | RNU1/2WCJ-4.7 | 1 | 453530474T | |
| PCB1 | R910 | METAL O R | RS1/2WBJ-10 | 1 | 443521004T | |
| PCB1 | R911 | METAL R | RNU1/2WCJ-0.47 | 1 | 453534794T | |
| PCB1 | R927 | METAL O R | RS1/2WBJ-27 | 1 | 443522704T | |
| PCB1 | R928 | METAL O R | RS1/2WBJ-27 | 1 | 443522704T | |
| PCB1 | R941 | METAL O R | RS1/2WBJ-22 | 1 | 443522204T | |
| PCB1 | R942 | C-CARBON R | RN72K1J-822JE | 1 | 435038224R1 | |
| PCB1 | R943 | C-CARBON R | RN72K1J-822JE | 1 | 435038224R1 | |
| PCB1 | R944 | C-CARBON R | RN72K1J-333JE | 1 | 435033334R1 | |
| PCB1 | R945 | DIODE | RL1N4003 | 1 | 22380260T | |
| PCB1 | R946 | METAL R | RNU1/2WCJ-2.2 | 1 | 453530224T | |
| PCB1 | R951 | METAL R | RNU1/2WCJ-0.1 | 1 | 453531094T | |
| PCB1 | R953 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R954 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R956 | C-CARBON R | RN72K1J-332JE | 1 | 435033324R1 | |
| PCB1 | R2244 | C-CARBON R | RN72K1J-122JE | 1 | 435031224R1 | |
| PCB1 | R2245 | C-CARBON R | RN72K1J-122JE | 1 | 435031224R1 | |
| PCB1 | R2246 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R2247 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R2248 | C-CARBON R | RN72K1J-224JE | 1 | 435032244R1 | |
| PCB1 | R2249 | C-CARBON R | RN72K1J-224JE | 1 | 435032244R1 | |
| PCB1 | R2250 | C-CARBON R | RN72K1J-272JE | 1 | 435032724R1 | |
| PCB1 | R2251 | C-CARBON R | RN72K1J-272JE | 1 | 435032724R1 | |
| PCB1 | R2252 | C-CARBON R | RN72K1J-682JE | 1 | 435036824R1 | |
| PCB1 | R2253 | C-CARBON R | RN72K1J-682JE | 1 | 435036824R1 | |
| PCB1 | R2254 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R2255 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB1 | R2256 | C-CARBON R | RN72K1J-472JE | 1 | 435034724R1 | |
| PCB1 | R2257 | C-CARBON R | RN72K1J-472JE | 1 | 435034724R1 | |
| PCB1 | R2258 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R2259 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB1 | R2260 | C-CARBON R | RN72K1J-224JE | 1 | 435032244R1 | |
| PCB1 | R2261 | C-CARBON R | RN72K1J-224JE | 1 | 435032244R1 | |
| PCB1 | R2262 | C-CARBON R | RN72K1J-224JE | 1 | 435032244R1 | |
| PCB1 | R2263 | C-CARBON R | RN72K1J-184JE | 1 | 435031844R1 | |
| PCB1 | R2264 | METAL O R | RS1/2WBJ-22 | 1 | 443522204T | |
| PCB1 | R2265 | METAL O R | RS1/2WBJ-22 | 1 | 443522204T | |
| PCB1 | R7101 | C-CARBON R | RN72K1J-561JE | 1 | 435035614R1 | <DAB MPB> |
| PCB1 | R7102 | C-CARBON R | RN72K1J-561JE | 1 | 435035614R1 | <DAB MPB> |
| PCB1 | R7103 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <DAB MPB> |
| PCB1 | R7104 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | <DAB MPB> |
| PCB1 | R7105 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | <DAB MPB> |
| PCB1 | R7107 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | <DAB MPB> |
| PCB1 | R7111 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | <DAB MPB> |
| PCB1 | R7112 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | <DAB MPB> |
| PCB1 | R8002 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8003 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8004 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB1 | R8005 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8006 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8007 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8009 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8010 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8012 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8013 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8014 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8015 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8016 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8017 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8018 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8019 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8020 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8021 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | R8022 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB1 | P204 | PLUG | NPLG-6P134 | 1 | 25055150 | |
| PCB1 | P206 | PLUG | NPLG-5P133 | 1 | 25055149 | |
| PCB1 | P207 | SOCKET | 16FMZ-ST | 1 | 25053093 | |
| PCB1 | P208 | PLUG | NPLG-2P29 | 1 | 25055038 | |
| PCB1 | P331A | SOCKET | NSCT-12P1027 | 1 | 25051237 | |
| PCB1 | P331B | PLUG | NPLG-12P664 | 1 | 25055708 | |
| PCB1 | P332A | SOCKET | NSCT-20P1031 | 1 | 25051241 | |
| PCB1 | P332B | PLUG | NPLG-20P668 | 1 | 25055712 | |
| PCB1 | P401 | PIN JACK | NPJ-6PDWWWRRR561 | 1 | 25045779 | |
| PCB1 | P401 or | PIN JACK | NPJ-6PDRW386 | (1) | 25045571 | |
| PCB1 | P401 or | PIN JACK | NPJ-6PDBL279 | (1) | 25045458 | |
| PCB1 | P403 | ST JACK | LGY2502-0200FC | 1 | 25045696 | |
| PCB1 | P499A | SOCKET | NSCT-5P1020 | 1 | 25051230 | |
| PCB1 | P499B | PLUG | NPLG-5P657 | 1 | 25055701 | |
| PCB1 | P771A | SOCKET | NSCT-6P1021 | 1 | 25051231 | |
| PCB1 | P771B | PLUG | NPLG-6P658 | 1 | 25055702 | |
| PCB1 | P903 | PLUG | NPLG-2P116 | 1 | 25055132 | |
| PCB1 | P905A | PLUG | NPLG-4P118 | 1 | 25055134 | |
| PCB1 | P941 | PLUG | NPLG-4P118 | 1 | 25055134 | |
| PCB1 | P1101A | SOCKET | NSCT-13P2106 | 1 | 25052209 | |
| PCB1 | P7001 | SOCKET | NSCT-18P2409 | 1 | 25052512 | |
| PCB1 | P7102A | SOCKET | NSCT-9P1024 | 1 | 25051234 | <DAB MPB> |
| PCB1 | P7102B | PLUG | NPLG-9P661 | 1 | 25055705 | <DAB MPB> |
| PCB1 | P7103 | PLUG | 9210B-2-44Z653-PT1 | 1 | 25056582 | <DAB MPB> |
| PCB1 | E001 | WS CLAMP | CB-71683(L=50) | 1 | 260261 | <DAB MPB> |
| PCB1 | J1 | PVC | 1007#24 .2/7HAND B | 1 | --- | NSP |
| PCB1 | J3 | PVC | 1007#24 .2/7HAND B | 1 | --- | NSP |
| PCB1 | J4 | PVC | 1007#24 .2/7HAND B | 1 | --- | NSP |
| PCB1 | J5 | PVC | 1007#24 .2/7HAND B | 1 | --- | NSP |
| PCB1 | J6 | PVC | 1007#24 .2/7HAND B | 1 | --- | NSP |
| PCB1 | JL902 | SOCKET | NSCT-6P98 | 1 | 25050270 | |
| PCB1 | JL4101B | WIRE TRAP | NPLG-7P590 | 1 | 25055628 | |
| PCB1 | JL503B | WIRE TRAP | NPLG-3P586 | 1 | 25055624 | |
| PCB1 | A101 | TAPE | TAPE(CLOTH-8U) | (1) | 29110082 | |

| | |
|---|---|
| **U05** | **DISPLAY PC BOARD (NADIS-8935-1A / 1B / 1C / 1D / 1E / 1F)** |
| **U06** | **POWER AMPLIFIER PC BOARD (NAAF-8936-1A / 1B / 1C / 1D / 1E / 1F)** |
| **U07** | **POWER SUPPLY PC BOARD (NAPS-8937-1A / 1B / 1C / 1D / 1E / 1F)** |
| **U08** | **SPEAKER TERMINAL PC BOARD (NAETC-8938-1B)** |
| **U09** | **SPEAKER TERMINAL PC BOARD (NAETC-8939-1A / 1C / 1D / 1E / 1F)** |

<Note1> U08 : MDC Only
<Note2> U09 : MPP, MGT, MDT, MGQ, DAB MPB Only

| | CIRCUIT NO. | PART NAME | DESCRIPTION | Q'TY | PART NO. (SN) | REMARKS |
|---|---|---|---|---|---|---|
| PCB2 | U801 | REMO SENS | GP1UM271XK0FH=12MM | 1 | 241360 | |
| PCB2 | Q802 | FL TUBE | 14-ST-56GNK | 1 | 212261 | |
| PCB2 | Q802A | HOLDER | (FL) | 1 | 27191281 | |
| PCB2 | Q801 | IC | UPD780232GC-091-8BT-A | 1 | 22241989R3 | |
| PCB2 | Q491 | TR | RN1441 | 1 | 2215410R2 | |
| PCB2 | Q492 | TR | RN1441 | 1 | 2215410R2 | |
| PCB2 | Q493 | TR | RN1441 | 1 | 2215410R2 | |
| PCB2 | Q494 | TR | RN1441 | 1 | 2215410R2 | |
| PCB2 | Q501 | TR | 2SC1622A(D17) | 1 | 2216153R2 | |
| PCB2 | Q501 or | TR | 2SC1622A-T-AZ | (1) | 2216154R2 | |
| PCB2 | Q501 or | TR | 2SC2713-BL | (1) | 2213136R2 | |
| PCB2 | Q502 | TR | 2SC1622A(D17) | 1 | 2216153R2 | |
| PCB2 | Q502 or | TR | 2SC1622A-T-AZ | (1) | 2216154R2 | |
| PCB2 | Q502 or | TR | 2SC2713-BL | (1) | 2213136R2 | |
| PCB2 | Q503 | TR | 2SC1622A(D17) | 1 | 2216153R2 | |
| PCB2 | Q503 or | TR | 2SC1622A-T-AZ | (1) | 2216154R2 | |
| PCB2 | Q503 or | TR | 2SC2713-BL | (1) | 2213136R2 | |
| PCB2 | Q504 | TR | 2SC1622A(D17) | 1 | 2216153R2 | |
| PCB2 | Q504 or | TR | 2SC1622A-T-AZ | (1) | 2216154R2 | |
| PCB2 | Q504 or | TR | 2SC2713-BL | (1) | 2213136R2 | |
| PCB2 | Q505 | TR | 2SC2712-GR | 1 | 2213145R2 | |
| PCB2 | Q506 | TR | 2SC2712-GR | 1 | 2213145R2 | |
| PCB2 | Q509 | TR | 2SA1015-GR | 1 | 2211455T | |
| PCB2 | Q510 | TR | 2SA1015-GR | 1 | 2211455T | |
| PCB2 | Q511 | TR | 2SA1015-GR | 1 | 2211455T | |
| PCB2 | Q512 | TR | 2SA1015-GR | 1 | 2211455T | |
| PCB2 | Q515 | TR | 2SA1015-GR | 1 | 2211455T | |
| PCB2 | Q516 | TR | 2SA1015-GR | 1 | 2211455T | |
| PCB2 | Q517 | TR | 2SC1815-GR | 1 | 2211255T | |
| PCB2 | Q518 | TR | 2SC1815-GR | 1 | 2211255T | |
| PCB2 | Q519 | TR | 2SC1815-GR | 1 | 2211255T | |
| PCB2 | Q520 | TR | 2SC1815-GR | 1 | 2211255T | |
| PCB2 | Q551 | TR | 2SC2712-GR | 1 | 2213145R2 | |
| PCB2 | Q552 | TR | 2SC2712-GR | 1 | 2213145R2 | |
| PCB2 | Q553 | TR | 2SC2235-O(TPE6_F) | 1 | 2211653T | |
| PCB2 | Q554 | TR | 2SC2235-O(TPE6_F) | 1 | 2211653T | |
| PCB2 | Q555 | TR | 2SA965-O(TPE6_F) | 1 | 2211643T | |
| PCB2 | Q556 | TR | 2SA965-O(TPE6_F) | 1 | 2211643T | |
| PCB2 | Q561 | TR | 2SA1162-GR | 1 | 2214375R2 | |
| PCB2 | Q562 | TR | 2SA1162-GR | 1 | 2214375R2 | |
| PCB2 | Q581 | TR | 2SC2712-GR | 1 | 2213145R2 | |
| PCB2 | Q582 | TR | 2SC2712-GR | 1 | 2213145R2 | |
| PCB2 | Q583 | TR | 2SA1015-GR | 1 | 2211455T | |
| PCB2 | Q803 | TR | 2SC2712-GR | 1 | 2213145R2 | |
| PCB2 | Q804 | TR | 2SC2712-GR | 1 | 2213145R2 | |
| PCB2 | Q901 | TR | DTC123JKA | 1 | 2216690R2 | |
| PCB2 | D501 | C-DIODE | 1SS355 | 1 | 223269R2 | |
| PCB2 | D502 | C-DIODE | 1SS355 | 1 | 223269R2 | |
| PCB2 | D503 | ZENER D | UDZS5.6B | 1 | 224550560R2 | |
| PCB2 | D504 | ZENER D | UDZS5.6B | 1 | 224550560R2 | |
| PCB2 | D581 | ZENER D | UDZS5.1B | 1 | 224550510R2 | |
| PCB2 | D801 | ZENER D | UDZS5.6B | 1 | 224550560R2 | |

www.audiodna.sk

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB2 | D811 | LED | SLI-343URC-T32 | 1 | 225436T | |
| PCB2 | D902 | C-DIODE | 1SS355 | 1 | 223269R2 | |
| PCB2 | D903 | C-DIODE | 1SS355 | 1 | 223269R2 | |
| PCB2 | D904 | C-DIODE | 1SS355 | 1 | 223269R2 | |
| PCB2 | D981 | DIODE | D3SBA20 | 1 | 22380271F | |
| PCB2 | D981 or | DIODE | RBV402 | (1) | 22380022F | |
| PCB2 | X801 | CERA LOCK | CSTLS5M00G56-A0 | 1 | 3010406T | |
| PCB2 | T902 | P TRANS | NPT-1519GQ | 1 | 2301811 | !, <MPP> |
| PCB2 | T902 | P TRANS | NPT-1520JQ | 1 | 2301812 | !, <MDC> |
| PCB2 | T902 | P TRANS | NPT-1519GQ | 1 | 2301811 | !, <MGT> |
| PCB2 | T902 | P TRANS | NPT-1520JQ | 1 | 2301812 | !, <MDT> |
| PCB2 | T902 | P TRANS | NPT-1519GQ | 1 | 2301811 | !, <MGQ> |
| PCB2 | T902 | P TRANS | NPT-1519GQ | 1 | 2301811 | !, <DAB MPB> |
| PCB2 | L571 | S COIL | S-1.3C | 1 | 231176S | <MPP> |
| PCB2 | L571 | S COIL | S-1.3C | 1 | 231176S | <MGT> |
| PCB2 | L571 | S COIL | S-1.3C | 1 | 231176S | <MDT> |
| PCB2 | L571 | S COIL | S-1.3C | 1 | 231176S | <MGQ> |
| PCB2 | L571 | S COIL | S-1.3C | 1 | 231176S | <DAB MPB> |
| PCB2 | L572 | S COIL | S-1.3C | 1 | 231176S | <MPP> |
| PCB2 | L572 | S COIL | S-1.3C | 1 | 231176S | <MGT> |
| PCB2 | L572 | S COIL | S-1.3C | 1 | 231176S | <MDT> |
| PCB2 | L572 | S COIL | S-1.3C | 1 | 231176S | <MGQ> |
| PCB2 | L572 | S COIL | S-1.3C | 1 | 231176S | <DAB MPB> |
| PCB2 | L573 | S COIL | S-1.3C | 1 | 231176S | <MDC> |
| PCB2 | L574 | S COIL | S-1.3C | 1 | 231176S | <MDC> |
| PCB2 | L801 | CHOKE COIL | NCH-1475 | 1 | 231237K100R2 | |
| PCB2 | L802 | CHOKE COIL | NCH-1475 | 1 | 231237K100R2 | |
| PCB2 | L873 | EMIFIL | BK1608LM182-T | 1 | 230958R1 | |
| PCB2 | L874 | EMIFIL | BK1608LM182-T | 1 | 230958R1 | |
| PCB2 | L875 | EMIFIL | BK1608LM182-T | 1 | 230958R1 | |
| PCB2 | L881 | EMIFIL | BK1608LM182-T | 1 | 230958R1 | |
| PCB2 | L882 | EMIFIL | BK1608LM182-T | 1 | 230958R1 | |
| PCB2 | L883 | EMIFIL | BK1608LM182-T | 1 | 230958R1 | |
| PCB2 | L901 | CHOKE COIL | NCH-3567 | 1 | 231287 | ! |
| PCB2 | C501 | VX C | CE04W50V 47M(VX_BLK) | 1 | 397384707T | |
| PCB2 | C502 | VX C | CE04W50V 47M(VX_BLK) | 1 | 397384707T | |
| PCB2 | C503 | TF C | ECQ-B50V-221K | 1 | 374722215T | |
| PCB2 | C504 | TF C | ECQ-B50V-221K | 1 | 374722215T | |
| PCB2 | C505 | VX C | CE04W50V-22M(VX_BLK) | 1 | 397382207T | |
| PCB2 | C506 | VX C | CE04W50V-22M(VX_BLK) | 1 | 397382207T | |
| PCB2 | C509 | VX C | CE04W10V-220M(VX_BLK) | 1 | 397332217T | |
| PCB2 | C510 | VX C | CE04W10V-220M(VX_BLK) | 1 | 397332217T | |
| PCB2 | C517 | VX C | CE04W50V-10M(VX_BLK) | 1 | 397381007T | |
| PCB2 | C518 | VX C | CE04W50V-10M(VX_BLK) | 1 | 397381007T | |
| PCB2 | C525 | C-CERA C | CC725CH1H-220J1 | 1 | 342102204R1 | |
| PCB2 | C526 | C-CERA C | CC725CH1H-220J1 | 1 | 342102204R1 | |
| PCB2 | C541 | VX C | CE04W50V-220M(VX_BLK) | 1 | 397382217T | |
| PCB2 | C542 | VX C | CE04W50V-220M(VX_BLK) | 1 | 397382217T | |
| PCB2 | C551 | VX C | CE04W50V-10M(VX_BLK) | 1 | 397381007T | |
| PCB2 | C552 | VX C | CE04W50V-10M(VX_BLK) | 1 | 397381007T | |
| PCB2 | C553 | TF C | ECQ-V50V-473J | 1 | 374724734T | |
| PCB2 | C554 | TF C | ECQ-V50V-473J | 1 | 374724734T | |
| PCB2 | C571 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MPP> |
| PCB2 | C571 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MGT> |
| PCB2 | C571 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MDT> |
| PCB2 | C571 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MGQ> |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB2 | C571 | TF C | ECQ-B50V-102J | 1 | 374721024T | <DAB MPB> |
| PCB2 | C572 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MPP> |
| PCB2 | C572 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MGT> |
| PCB2 | C572 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MDT> |
| PCB2 | C572 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MGQ> |
| PCB2 | C572 | TF C | ECQ-B50V-102J | 1 | 374721024T | <DAB MPB> |
| PCB2 | C573 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MPP> |
| PCB2 | C573 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MGT> |
| PCB2 | C573 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MDT> |
| PCB2 | C573 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MGQ> |
| PCB2 | C573 | TF C | ECQ-B50V-102J | 1 | 374721024T | <DAB MPB> |
| PCB2 | C574 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MPP> |
| PCB2 | C574 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MGT> |
| PCB2 | C574 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MDT> |
| PCB2 | C574 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MGQ> |
| PCB2 | C574 | TF C | ECQ-B50V-102J | 1 | 374721024T | <DAB MPB> |
| PCB2 | C575 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MPP> |
| PCB2 | C575 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MGT> |
| PCB2 | C575 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MDT> |
| PCB2 | C575 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MGQ> |
| PCB2 | C575 | TF C | ECQ-B50V-102J | 1 | 374721024T | <DAB MPB> |
| PCB2 | C583 | VX C | CE04W50V-1M(VX_BLK) | 1 | 397380107T | |
| PCB2 | C592 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MDC> |
| PCB2 | C593 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MDC> |
| PCB2 | C594 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MDC> |
| PCB2 | C595 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MDC> |
| PCB2 | C596 | TF C | ECQ-B50V-102J | 1 | 374721024T | <MDC> |
| PCB2 | C801 | ELECT C | CE04W16V-47M | 1 | 355744709T | |
| PCB2 | C802 | C-CERA C | CK725F1H-224Z1 | 1 | 332152240R1 | |
| PCB2 | C806 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB2 | C807 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB2 | C809 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB2 | C810 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB2 | C811 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB2 | C812 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB2 | C815 | C-CERA C | CC725CH1H-330J1 | 1 | 342103304R1 | |
| PCB2 | C816 | C-CERA C | CC725CH1H-330J1 | 1 | 342103304R1 | |
| PCB2 | C817 | C-CERA C | CC725CH1H-330J1 | 1 | 342103304R1 | |
| PCB2 | C818 | C-CERA C | CC725CH1H-330J1 | 1 | 342103304R1 | |
| PCB2 | C819 | C-CERA C | CC725CH1H-330J1 | 1 | 342103304R1 | |
| PCB2 | C820 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB2 | C821 | ELECT C | CE04W16V-47M | 1 | 355744709T | |
| PCB2 | C823 | C-CERA C | CC725CH1H-221J1 | 1 | 342102214R1 | |
| PCB2 | C824 | C-CERA C | CC725CH1H-221J1 | 1 | 342102214R1 | |
| PCB2 | C871 | C-CERA C | CC725CH1H-102J1 | 1 | 342101024R1 | |
| PCB2 | C872 | C-CERA C | CC725CH1H-102J1 | 1 | 342101024R1 | |
| PCB2 | C873 | C-CERA C | CK725F1H-103Z1 | 1 | 332151030R1 | |
| PCB2 | C874 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB2 | C878 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB2 | C881 | C-CERA C | CC725CH1H-221J1 | 1 | 342102214R1 | |
| PCB2 | C882 | C-CERA C | CC725CH1H-221J1 | 1 | 342102214R1 | |
| PCB2 | C885 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB2 | C901 | IS C | DE1007E472M-KY | 1 | 3300063 | ! |
| PCB2 | C902 | IS C | DE1007E472M-KY | 1 | 3300063 | ! |
| PCB2 | C903 | IS C | DE1007E472M-KY | 1 | 3300063 | ! |
| PCB2 | C904 | TF C | ECQ-B50V-223J | 1 | 3747222347 | |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB2 | C909 | VX C | CE04W50V-4.7M(VX_BLK) | 1 | 397380477T | |
| PCB2 | C914 | C-CERA C | CK725F1H-104Z1 | 1 | 332151040R1 | |
| PCB2 | C961 | TF C | ECQ-V50V-104J | 1 | 374721044T | |
| PCB2 | C981 | TF C | ECQ-V50V-334J | 1 | 374723344T | |
| PCB2 | C982 | TF C | ECQ-V50V-334J | 1 | 374723344T | |
| PCB2 | C983 | ELECT C | CE04W25V-3300M(RZ) | 1 | 3504447S | |
| PCB2 | C984 | ELECT C | CE04W25V-3300M(RZ) | 1 | 3504447S | |
| PCB2 | R501 | C-CARBON R | RN72K1J-333JE | 1 | 435033334R1 | |
| PCB2 | R502 | C-CARBON R | RN72K1J-333JE | 1 | 435033334R1 | |
| PCB2 | R503 | C-CARBON R | RN72K1J-123JE | 1 | 435031234R1 | |
| PCB2 | R504 | C-CARBON R | RN72K1J-123JE | 1 | 435031234R1 | |
| PCB2 | R505 | C-CARBON R | RN72K1J-223JE | 1 | 435032234R1 | |
| PCB2 | R506 | C-CARBON R | RN72K1J-223JE | 1 | 435032234R1 | |
| PCB2 | R507 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |
| PCB2 | R508 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |
| PCB2 | R509 | C-CARBON R | RN72K1J-821JE | 1 | 435038214R1 | |
| PCB2 | R510 | C-CARBON R | RN72K1J-821JE | 1 | 435038214R1 | |
| PCB2 | R511 | C-CARBON R | RN72K1J-821JE | 1 | 435038214R1 | |
| PCB2 | R512 | C-CARBON R | RN72K1J-821JE | 1 | 435038214R1 | |
| PCB2 | R513 | C-CARBON R | RN72K1J-332JE | 1 | 435033324R1 | |
| PCB2 | R514 | C-CARBON R | RN72K1J-332JE | 1 | 435033324R1 | |
| PCB2 | R515 | C-CARBON R | RN72K1J-821JE | 1 | 435038214R1 | |
| PCB2 | R516 | C-CARBON R | RN72K1J-821JE | 1 | 435038214R1 | |
| PCB2 | R517 | C-CARBON R | RN72K1J-333JE | 1 | 435033334R1 | |
| PCB2 | R518 | C-CARBON R | RN72K1J-333JE | 1 | 435033334R1 | |
| PCB2 | R519 | METAL O R | RS1/2WBJ-39 | 1 | 443523904T | |
| PCB2 | R520 | METAL O R | RS1/2WBJ-39 | 1 | 443523904T | |
| PCB2 | R521 | METAL O R | RS1/2WBJ-39 | 1 | 443523904T | |
| PCB2 | R522 | METAL O R | RS1/2WBJ-39 | 1 | 443523904T | |
| PCB2 | R523 | C-CARBON R | RN72K1J-682JE | 1 | 435036824R1 | |
| PCB2 | R524 | C-CARBON R | RN72K1J-682JE | 1 | 435036824R1 | |
| PCB2 | R525 | C-CARBON R | RN72K1J-183JE | 1 | 435031834R1 | |
| PCB2 | R526 | C-CARBON R | RN72K1J-183JE | 1 | 435031834R1 | |
| PCB2 | R527 | C-CARBON R | RN72K1J-183JE | 1 | 435031834R1 | |
| PCB2 | R528 | C-CARBON R | RN72K1J-183JE | 1 | 435031834R1 | |
| PCB2 | R533 | METAL O R | RS1/2WBJ-33 | 1 | 443523304T | |
| PCB2 | R534 | METAL O R | RS1/2WBJ-33 | 1 | 443523304T | |
| PCB2 | R535 | METAL O R | RS1/2WBJ-39 | 1 | 443523904T | |
| PCB2 | R536 | METAL O R | RS1/2WBJ-39 | 1 | 443523904T | |
| PCB2 | R537 | C-CARBON R | RN72K1J-181JE | 1 | 435031814R1 | |
| PCB2 | R538 | C-CARBON R | RN72K1J-181JE | 1 | 435031814R1 | |
| PCB2 | R539 | C-CARBON R | RN72K1J-181JE | 1 | 435031814R1 | |
| PCB2 | R540 | C-CARBON R | RN72K1J-181JE | 1 | 435031814R1 | |
| PCB2 | R541 | METAL O R | RS1/2WBJ-22 | 1 | 443522204T | |
| PCB2 | R542 | METAL O R | RS1/2WBJ-22 | 1 | 443522204T | |
| PCB2 | R543 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |
| PCB2 | R544 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |
| PCB2 | R545 | METAL O R | RS1/2WBJ-10 | 1 | 443521004T | <MDC> |
| PCB2 | R546 | METAL O R | RS1/2WBJ-10 | 1 | 443521004T | <MDC> |
| PCB2 | R547 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MDC> |
| PCB2 | R548 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MDC> |
| PCB2 | R549 | C-CARBON R | RN72K1J-681JE | 1 | 435036814R1 | <MDC> |
| PCB2 | R551 | C-CARBON R | RN72K1J-152FE | 1 | 435031522R1 | |
| PCB2 | R552 | C-CARBON R | RN72K1J-152FE | 1 | 435031522R1 | |
| PCB2 | R553 | C-CARBON R | RN72K1J-681FE | 1 | 435036812R1 | |
| PCB2 | R554 | C-CARBON R | RN72K1J-681FE | 1 | 435036812R1 | |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB2 | R555 | C-CARBON R | RN72K1J-472FE | 1 | 435034722R1 | |
| PCB2 | R556 | C-CARBON R | RN72K1J-472FE | 1 | 435034722R1 | |
| PCB1 | <Note> | | | | | |
| PCB1 | Circuit No. : R551 - R556 ---> Resistance tolerance : F class (+1 / -1 %) | | | | | |
| PCB2 | R557 | METAL O R | RS1/2WBJ-82 | 1 | 443528204T | |
| PCB2 | R558 | METAL O R | RS1/2WBJ-82 | 1 | 443528204T | |
| PCB2 | R559 | METAL R | RNU2WCJ-0.22 | 1 | 452732294F | |
| PCB2 | R560 | METAL R | RNU2WCJ-0.22 | 1 | 452732294F | |
| PCB2 | R561 | METAL R | RNU2WCJ-0.22 | 1 | 452732294F | |
| PCB2 | R562 | METAL R | RNU2WCJ-0.22 | 1 | 452732294F | |
| PCB2 | R563 | METAL R | RNU1/2WCJ-8.2 | 1 | 453530824T | |
| PCB2 | R564 | METAL R | RNU1/2WCJ-8.2 | 1 | 453530824T | |
| PCB2 | R565 | C-CARBON R | RN72K1J-101FE | 1 | 435031012R1 | |
| PCB2 | R566 | C-CARBON R | RN72K1J-101FE | 1 | 435031012R1 | |
| PCB2 | R571 | METAL O R | RS1/2WBJ-10 | 1 | 443521004T | <MPP> |
| PCB2 | R571 | METAL O R | RS1/2WBJ-10 | 1 | 443521004T | <MGT> |
| PCB2 | R571 | METAL O R | RS1/2WBJ-10 | 1 | 443521004T | <MDT> |
| PCB2 | R571 | METAL O R | RS1/2WBJ-10 | 1 | 443521004T | <MGQ> |
| PCB2 | R571 | METAL O R | RS1/2WBJ-10 | 1 | 443521004T | <DAB MPB> |
| PCB2 | R572 | METAL O R | RS1/2WBJ-10 | 1 | 443521004T | <MPP> |
| PCB2 | R572 | METAL O R | RS1/2WBJ-10 | 1 | 443521004T | <MGT> |
| PCB2 | R572 | METAL O R | RS1/2WBJ-10 | 1 | 443521004T | <MDT> |
| PCB2 | R572 | METAL O R | RS1/2WBJ-10 | 1 | 443521004T | <MGQ> |
| PCB2 | R572 | METAL O R | RS1/2WBJ-10 | 1 | 443521004T | <DAB MPB> |
| PCB2 | R573 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MPP> |
| PCB2 | R573 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MGT> |
| PCB2 | R573 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MDT> |
| PCB2 | R573 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MGQ> |
| PCB2 | R573 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <DAB MPB> |
| PCB2 | R574 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MPP> |
| PCB2 | R574 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MGT> |
| PCB2 | R574 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MDT> |
| PCB2 | R574 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <MGQ> |
| PCB2 | R574 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | <DAB MPB> |
| PCB2 | R575 | C-CARBON R | RN72K1J-681JE | 1 | 435036814R1 | <MPP> |
| PCB2 | R575 | C-CARBON R | RN72K1J-681JE | 1 | 435036814R1 | <MGT> |
| PCB2 | R575 | C-CARBON R | RN72K1J-681JE | 1 | 435036814R1 | <MDT> |
| PCB2 | R575 | C-CARBON R | RN72K1J-681JE | 1 | 435036814R1 | <MGQ> |
| PCB2 | R575 | C-CARBON R | RN72K1J-681JE | 1 | 435036814R1 | <DAB MPB> |
| PCB2 | R577 | C-CARBON R | RN72K1J-561JE | 1 | 435035614R1 | |
| PCB2 | R578 | C-CARBON R | RN72K1J-561JE | 1 | 435035614R1 | |
| PCB2 | R581 | C-CARBON R | RN72K1J-123JE | 1 | 435031234R1 | |
| PCB2 | R582 | C-CARBON R | RN72K1J-123JE | 1 | 435031234R1 | |
| PCB2 | R583 | C-CARBON R | RN72K1J-562JE | 1 | 435035624R1 | |
| PCB2 | R584 | C-CARBON R | RN72K1J-562JE | 1 | 435035624R1 | |
| PCB2 | R585 | C-CARBON R | RN72K1J-333JE | 1 | 435033334R1 | |
| PCB2 | R586 | C-CARBON R | RN72K1J-333JE | 1 | 435033334R1 | |
| PCB2 | R587 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB2 | R588 | C-CARBON R | RN72K1J-183JE | 1 | 435031834R1 | |
| PCB2 | R589 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB2 | R597 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB2 | R598 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB2 | R801 | C-CARBON R | RN72K1J-104JE | 1 | 435031044R1 | |
| PCB2 | R802 | C-CARBON R | RN72K1J-104JE | 1 | 435031044R1 | |
| PCB2 | R803 | C-CARBON R | RN72K1J-104JE | 1 | 435031044R1 | |
| PCB2 | R804 | C-CARBON R | RN72K1J-104JE | 1 | 435031044R1 | |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB2 | R806 | C-CARBON R | RN72K1J-223JE | 1 | 435032234R1 | |
| PCB2 | R807 | C-CARBON R | RN72K1J-223JE | 1 | 435032234R1 | |
| PCB2 | R808 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB2 | R809 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB2 | R810 | C-CARBON R | RN72K1J-272JE | 1 | 435032724R1 | |
| PCB2 | R811 | C-CARBON R | RN72K1J-272JE | 1 | 435032724R1 | |
| PCB2 | R812 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB2 | R813 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB2 | R814 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB2 | R815 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |
| PCB2 | R816 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |
| PCB2 | R817 | C-CARBON R | RN72K1J-221JE | 1 | 435032214R1 | |
| PCB2 | R818 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |
| PCB2 | R819 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB2 | R820 | C-CARBON R | RN72K1J-105JE | 1 | 435031054R1 | |
| PCB2 | R824 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |
| PCB2 | R827 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB2 | R828 | C-CARBON R | RN72K1J-103JE | 1 | 435031034R1 | |
| PCB2 | R830 | C-CARBON R | RN72K1J-000JE | 1 | 435030004R1 | |
| PCB2 | R831 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB2 | R839 | C-CARBON R | RN72K1J-223JE | 1 | 435032234R1 | |
| PCB2 | R840 | C-CARBON R | RN72K1J-391JE | 1 | 435033914R1 | |
| PCB2 | R841 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |
| PCB2 | R842 | C-CARBON R | RN72K1J-821JE | 1 | 435038214R1 | |
| PCB2 | R843 | C-CARBON R | RN72K1J-102JE | 1 | 435031024R1 | |
| PCB2 | R846 | C-CARBON R | RN72K1J-391JE | 1 | 435033914R1 | |
| PCB2 | R853 | C-CARBON R | RN72K1J-391JE | 1 | 435033914R1 | |
| PCB2 | R854 | C-CARBON R | RN72K1J-471JE | 1 | 435034714R1 | |
| PCB2 | R858 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB2 | R859 | C-CARBON R | RN72K1J-101JE | 1 | 435031014R1 | |
| PCB2 | R860 | C-CARBON R | RN72K1J-332JE | 1 | 435033324R1 | |
| PCB2 | R884 | C-CARBON R | RN72K1J-563JE | 1 | 435035634R1 | |
| PCB2 | R885 | C-CARBON R | RN72K1J-563JE | 1 | 435035634R1 | |
| PCB2 | R886 | C-CARBON R | RN72K1J-331JE | 1 | 435033314R1 | |
| PCB2 | R887 | C-CARBON R | RN72K1J-331JE | 1 | 435033314R1 | |
| PCB2 | R888 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB2 | R889 | C-CARBON R | RN72K1J-473JE | 1 | 435034734R1 | |
| PCB2 | R893 | METAL O R | RS1/2WBJ-390 | 1 | 443523914T | |
| PCB2 | R894 | METAL O R | RS1/2WBJ-390 | 1 | 443523914T | |
| PCB2 | R901 | C-CARBON R | RN72K1J-333JE | 1 | 435033334R1 | |
| PCB2 | R902 | C-CARBON R | RN72K1J-153JE | 1 | 435031534R1 | |
| PCB2 | RL901 | RELAY | NRL-1P5A-DC9-179 | 1 | 25065669 | ! |
| PCB2 | S801 | R ENCODE | REB12305PVB-299-9092 | 1 | 25065688 | |
| PCB2 | S803 | PUSH SW | NPS-111-S681 | 1 | 25035718T | |
| PCB2 | S804 | PUSH SW | NPS-111-S681 | 1 | 25035718T | |
| PCB2 | S805 | PUSH SW | NPS-111-S681 | 1 | 25035718T | |
| PCB2 | S806 | PUSH SW | NPS-111-S681 | 1 | 25035718T | |
| PCB2 | S807 | PUSH SW | NPS-111-S681 | 1 | 25035718T | |
| PCB2 | S811 | PUSH SW | NPS-111-S681 | 1 | 25035718T | |
| PCB2 | S821 | PUSH SW | NPS-111-S681 | 1 | 25035718T | |
| PCB2 | S822 | PUSH SW | NPS-111-S681 | 1 | 25035718T | |
| PCB2 | S823 | PUSH SW | NPS-111-S681 | 1 | 25035718T | |
| PCB2 | P501 | TRM | NTM-4PDMN384 | 1 | 25060455 | <MPP> |
| PCB2 | P501 or | TRM | NTM-4PDMN226 | (1) | 25060295 | <MPP> |
| PCB2 | P501 | TRM | NTM-4PDMN384 | 1 | 25060455 | <MGT> |
| PCB2 | P501 or | TRM | NTM-4PDMN226 | (1) | 25060295 | <MGT> |

| | | | | | | |
|---|---|---|---|---|---|---|
| PCB2 | P501 | TRM | NTM-4PDMN384 | 1 | 25060455 | <MDT> |
| PCB2 | P501 or | TRM | NTM-4PDMN226 | (1) | 25060295 | <MDT> |
| PCB2 | P501 | TRM | NTM-4PDMN384 | 1 | 25060455 | <MGQ> |
| PCB2 | P501 or | TRM | NTM-4PDMN226 | (1) | 25060295 | <MGQ> |
| PCB2 | P501 | TRM | NTM-4PDMN384 | 1 | 25060455 | <DAB MPB> |
| PCB2 | P501 or | TRM | NTM-4PDMN226 | (1) | 25060295 | <DAB MPB> |
| PCB2 | P502 | PIN JACK | NPJ-1PDBL382 | 1 | 25045567 | <MPP> |
| PCB2 | P502 | PIN JACK | NPJ-1PDBL382 | 1 | 25045567 | <MGT> |
| PCB2 | P502 | PIN JACK | NPJ-1PDBL382 | 1 | 25045567 | <MDT> |
| PCB2 | P502 | PIN JACK | NPJ-1PDBL382 | 1 | 25045567 | <MGQ> |
| PCB2 | P502 | PIN JACK | NPJ-1PDBL382 | 1 | 25045567 | <DAB MPB> |
| PCB2 | P504 | TRM | NTM-4PDML237 | 1 | 25060306 | <MDC> |
| PCB2 | P505 | PIN JACK | NPJ-1PDBL382 | 1 | 25045567 | <MDC> |
| PCB2 | P7001A | SOCKET | NSCT-18P2436 | 1 | 25052539 | |
| PCB2 | P871 | JACK | LGT1516-0101 | 1 | 25045396 | |
| PCB2 | P873 | CRIMP AS | CRIMP AS | 1 | 2067A12100 | |
| PCB2 | P874 | CRIMP AS | CRIMP AS | 1 | 2067A12100 | |
| PCB2 | P881 | JACK | LGT1516-0101 | 1 | 25045396 | |
| PCB2 | P901A | AC INLET | YKE31-0129 | 1 | 25053195 | !, <MPP> |
| PCB2 | P901A | AC INLET | YKE31-0129 | 1 | 25053195 | !, <MGT> |
| PCB2 | P901A | AC INLET | YKE31-0129 | 1 | 25053195 | !, <MGQ> |
| PCB2 | P901A | AC INLET | YKE31-0129 | 1 | 25053195 | !, <DAB MPB> |
| PCB2 | P901B | AC INLET | YKE31-0130 | 1 | 25053196 | !, <MDC> |
| PCB2 | P901B | AC INLET | YKE31-0130 | 1 | 25053196 | !, <MDT> |
| PCB2 | P904 | PLUG | NPLG-4P151 | 1 | 25055167 | |
| PCB2 | P921B | PLUG | NPLG-2P631 | 1 | 25055675 | ! |
| PCB2 | F901A | FUSE HOL | NSCT-1P2031 | 1 | 25052133T | ! |
| PCB2 | F901B | FUSE HOL | NSCT-1P2031 | 1 | 25052133T | ! |
| PCB2 | F901C | FUSE LABEL | 1.25A125V | 1 | 29364667 | !, <MDC> |
| PCB2 | JL4101 | JUMPER LEAD | JL7 100 B | 1 | --- | NSP, <MPP> |
| PCB2 | JL4101 | JUMPER LEAD | JL7 100 B | 1 | --- | NSP, <MDC> |
| PCB2 | JL4101 | JUMPER LEAD | JL7 100 B | 1 | --- | NSP, <MGT> |
| PCB2 | JL4101 | JUMPER LEAD | JL7 100 B | 1 | --- | NSP, <MDT> |
| PCB2 | JL4101 | JUMPER LEAD | JL7 100 B | 1 | --- | NSP, <MGQ> |
| PCB2 | JL4101A | WIRE HOL | NSCT-7P878 | 1 | 25051091 | |
| PCB2 | JL4101C | JUMPER LEAD | JL7 150 UL2651#24 | 1 | 7J150606B15 | NSP, <DAB MPB> |
| PCB2 | JL501 | JUMPER LEAD | JL4 150 H | 1 | 4J150606H | NSP |
| PCB2 | JL501A | WIRE HOL | NSCT-4P895 | 1 | 25051108 | |
| PCB2 | JL501B | WIRE HOL | NSCT-4P895 | 1 | 25051108 | <MPP> |
| PCB2 | JL501B | WIRE HOL | NSCT-4P895 | 1 | 25051108 | <MGT> |
| PCB2 | JL501B | WIRE HOL | NSCT-4P895 | 1 | 25051108 | <MDT> |
| PCB2 | JL501B | WIRE HOL | NSCT-4P895 | 1 | 25051108 | <MGQ> |
| PCB2 | JL501B | WIRE HOL | NSCT-4P895 | 1 | 25051108 | <DAB MPB> |
| PCB2 | JL501C | WIRE HOL | NSCT-4P895 | 1 | 25051108 | <MDC> |
| PCB2 | JL502 | JUMPER LEAD | JL 5 350 B | 1 | 5J350606B15 | NSP |
| PCB2 | JL502A | WIRE HOL | NSCT-5P876 | 1 | 25051089 | |
| PCB2 | JL502B | WIRE TRAP | NPLG-5P588 | 1 | 25055626 | <MPP> |
| PCB2 | JL502B | WIRE TRAP | NPLG-5P588 | 1 | 25055626 | <MGT> |
| PCB2 | JL502B | WIRE TRAP | NPLG-5P588 | 1 | 25055626 | <MDT> |
| PCB2 | JL502B | WIRE TRAP | NPLG-5P588 | 1 | 25055626 | <MGQ> |
| PCB2 | JL502B | WIRE TRAP | NPLG-5P588 | 1 | 25055626 | <DAB MPB> |
| PCB2 | JL502C | WIRE TRAP | NPLG-5P588 | 1 | 25055626 | <MDC> |
| PCB2 | JL503 | JUMPER LEAD | JL3 200 B | 1 | 3J200606B15 | NSP |
| PCB2 | JL503A | WIRE HOL | NSCT-3P874 | 1 | 25051087 | |
| PCB2 | JL902A | WIRE HOL | NSCT-6P897 | 1 | 25051110 | |
| PCB2 | JL902B | JUMPER LEAD | JL6 05 H | 1 | 6J050606H | NSP |

**ONKYO CORPORATION**
Sales & Product Planning Div. : 2-1, Nisshin-cho, Neyagawa-shi, OSAKA 572-8540, JAPAN
Tel: 072-831-8023 Fax: 072-831-8124

**ONKYO U.S.A. CORPORATION**
18 Park Way, Upper Saddle River, N.J. 07458, U.S.A.
Tel: 201-785-2600 Fax: 201-785-2650 http://www.us.onkyo.com/

**ONKYO EUROPE ELECTRONICS GmbH**
Liegnitzerstrasse 6, 82194 Groebenzell, GERMANY
Tel: +49-8142-4401-0 Fax: +49-8142-4401-555 http://www.eu.onkyo.com/

**ONKYO EUROPE UK Office**
Suite 1, Gregories Court, Gregories Road, Beaconsfield, Buckinghamshire, HP9 1HQ
UNITED KINGDOM Tel: +44-(0)1494-681515 Fax: +44(0)-1494-680452

**ONKYO CHINA LIMITED**
Units 2102-2107, Metroplaza Tower I, 223 Hing Fong Road, Kwai Chung,
N.T., HONG KONG Tel: 852-2429-3118 Fax: 852-2428-9039
http://www.ch.onkyo.com/

ONKYO
HOMEPAGE
**http://www.onkyo.com/**

www.audiodna.sk